or minimized. The trigger circuit delays the time base circuit operation. This makes the moving wave appears to be static (unmoved) on the screen. The frequency, wave length and amplitude can be measured, when it is unmoved (locked).

10.3.2. Classifications of C.R.O

1. Analog C.R.O
2. Digital C.R.O

10.3.3. Types of digital CRO

1. Digital Storage Oscilloscope
2. Digital Phosphor Oscilloscope
3. Sampling Oscilloscope
4. PC Based Oscilloscope

10.3.4. C.R.O Probes

A cable which is used to connect CRO and the circuit under test is known as CRO probe.

10.3.5. Applications of CRO

1. Various waveforms with reference to time can be measured.
2. It is used to align all the parts of TV receivers.
3. Signal voltage can be measured.
4. Used to rectify the faults in TV receivers.
5. Frequency of the Signal can be measured.
6. Faults in DVD can be rectified.
7. Phase shift of a signal can be measured.

10.4. SIGNAL GENERATOR

This instrument generates Audio Frequency (AF) and Radio Frequency (RF) signals. Hence, it is also called as AF and RF signal generator.

It is of two types

1. Analog Signal Generator
2. Digital Signal Generator

10.4.1. (a) Analog signal generator

It consists of the following sections.

RF Oscillator: This section generates fixed RF waves. This wave is known as carrier waves. Frequency of this wave can be altered by adjusting the variable capacitor (Gang).

RF Amplifier: It amplifies the RF signal.

AF Amplifier: This stage amplifies the AF signal. An output can be obtained through the socket AF-OUT, which is used to find faults appeared in audio stages of any receiver. The strength of AF can be altered by means of a potentiometer.

AF Oscillator: This will generate noiseless audio wave.

AM Modulator: In this section, the sound wave amplitude is modulated.

RF Amplifier: This amplifies the modulated signal and fed to the RF out.

In Radio receivers, faults can be rectified by using the modulated RF waves, when injecting into the RF and IF stages of Radio receivers. The strength of the signal can be varied through potentiometer.

10.4.1. (b) Front panel and handling methods of analog signal generator

Figure 10.22 shows the front panel of an analog signal generator. The functional description of each function of the signal generator is summarized as follows.

ELEC_EQUIP_Chapter10.indd 215 11/10/2020 11:55:37 AM