14. The thickness of the V_belt	8mm to 19mm
15. The efficiency of the V_belt	70% to 98%
16. Velocity ratio of a belt drive	$\frac{N_2}{N_1} = \frac{D_1}{D_2}$ D_1, D_2 are the diameter of driver and follower. N_1, N_2 are the number of revolutions perminute of the driver and follower.
17. Velocity ratio depends on	1. Thickness of the belt 2. Slip of the belt.
18. Belt slip (%) (s)	$S = \frac{\text{Estimated speed} - \text{Actual speed}}{\text{Estimated speed}} \times 100$
19. Velocity Ratio with considering slip	$\frac{N_2}{N_1} = \frac{D_1}{D_2} \times \left(\frac{100 - s}{100}\right)$
20. Spur gears	1. Gear teeths are parallel to the shaft axis. 2. These gears are used to Transmit power between Parallel shafts.
21. Helical gears	1. The teeth are inclined to the snaft axvis 2. They are smooth acting Because there will always engage More than one tooth in contact
22. Bevel gears	1. The teeth elements on The conieal surface. 2. The power is transmitted Between two shafts Which are at right angles Though bevel gears.
23. Rack and pinion gears	1. The rack gears are straight and flat and pinion are rotate. 2. This type of gear is used to convert rotary motion into linear motion or Vice versa
24. Worm and worm gears	1. worm may be single threaded or multi threaded. 2. This gearing is used where a large speed reduction. 3. Worm and worm gear are used to transmit power between two perpendicular (90°) shafts.
25. Two gears are rotates with each other	1. Driving gear rotates in the clockwise direction 2. The follower will rotate in the anti-clock wise direction.

GM_Chp09.indd 123 14-02-2019 11:43:59