PROCEDURE

- The preliminary adjustments are carried out as follows.
  a. The leveling screws at the base of TG are adjusted so that the circular turn table is horizontal and the plane of the circular coil is vertical.
  b. The circular coil is rotated so that its plane is in the magnetic meridian i.e., along the north-south direction.
  c. The compass box alone is rotated till the aluminium pointer reads $0° - 0°$.
- The connections are made as shown in Figure (c).
- The number of turns *n* is selected and the circuit is switched on.
- The range of current through TG is chosen in such a way that the deflection of the aluminium pointer lies between $30° - 60°$.
- A suitable current is allowed to pass through the circuit, the deflections θ_1 and θ_2 are noted from two ends of the aluminium pointer.
- Now the direction of current is reversed using commutator C, the deflections θ_3 and θ_4 in the opposite directions are noted.
- The mean value θ of θ_1, θ_2, θ_3 and θ_4 is calculated and tabulated.
- The reduction factor k is calculated for each case and it is found that k is a constant.
- The experiment is repeated for various values of current and the readings are noted and tabulated.
- The radius of the circular coil is found by measuring the circumference of the coil using a thread around the coil.
- From the values of *r*, *n* and *k*, the horizontal component of Earth's magnetic field is determined.

Commutator:



It is a kind of switch employed in electrical circuits, electric motors and electric generators. It is used to reverse the direction of current in the circuit.

XII-Physics_Vol-1) PRACTICAL.indd 292 14-02-2020 20:12:57