Defects	Reasons	Remedies
	4. Open circuit fault occurs.	Check the winding coils and correct it.
	5. The wrong connection of the coil.	Check the coil connection test and connect it properly.
	6. Check whether the brushes are having contacts with the slip rings.	Check the brush contacts properly
2. When the electric supply is given to the DC motors, the fuse wire is melted.	1. Over load.	Reduce the over load.
	2. Short-circuit in winding coils.	Check the winding coils, test and correct it.
	3. Short-circuit in supply voltage.	Test the supply voltage and correct it.
3. Get the electric shock when we touch the motors	1. Due to low insulation resisting winding coil touches the motor body.	Check the insulation resistance and insulate the motor.
	2. Coil touches the body (or) core.	Check the slot insulation and correct it properly.
4. Sparking at the commutator.	1. Low quality carbon brushes.	Quality brushes can be replaced.
	2. Pressure on the brushes are not proper.	Proper pressure should be applied.
	3. Wear and tear of brushes.	Brushes can be replaced.
5. Vibration in machines.	1. Motor is not fixed properly.	Proper fixation is to be made.
	2. No proper alignment.	Check the alignment.
	3. No proper balancing.	Check the balancing.
	4. Worn out bearings.	Replace the bearings.

10.4.2 General defects and remedies for AC motors

Sl. No.	Defects	Reasons	Remedies
1.	Motor not gets started.	1. Open circuit.	Trace the open circuit and correct it properly.
		2. Low voltage.	Operate with proper (or) rated voltage.
		3. Damaged rotor.	Replace the rotor.
		4. Over load.	Reduce the load.
		5. Bearings are fitted with tight.	Lubricate the bearings and check it.

BEE_ENG_Chapter_10.indd 158 12/27/2019 10:39:26 AM