Practical

5

Ceiling fan

AIM

1. To dismantle the given ceiling fan and identify the parts.
2. To test the ceiling fan, identify and rectify its faults, and assemble the ceiling fan.

Related information

The information of a ceiling fan is obtained from name plate which is fixed on the body of the fan. It helps us to know details of the fan correctly. Generally in ceiling fan, permanent capacitor induction run motor is used. The inner portion of ceiling fan is stator. The outer rotating portion is rotor. Ceiling fan is fitted in the ceiling by conduit metal pipe. When the power supply is given, the blade of the fan rotates and air is circulated around the area where the fan is connected. Regulator is connected in series with the motor to control the speed.

Tools required

Sl. No.	Hand tools	Quantity
1	Insulated cutting plier	1
2	Insulated screw driver 15 cm	1
3	Insulated screw driver 25 cm	1
4	Test lamp	1
5	Spanner set	1

Apparatus required

Sl. No.	Equipments	Quantity
1	Ceiling fan	1
2	Insulation tape	1
3	Grease	1 pocket
4	Kerosene	100 ml
5	Bearing puller	1
6	Waste cotton	Required quantity
7	Wooden board	Required quantity

Practical procedure

Dismantling

i. Separate the fan from ceiling clips.
ii. Unscrew the screws in canopy.
iii. Remove the condenser from its housing.

BEE_ENG_Pratical.indd 188 12/27/2019 10:54:34 AM