கோடிங்

```
/* Code for multiple LEDs*/
int timer = 100; // The higher the number, the slower the timing.
intledPins[] = {
2, 7, 4, 6, 5, 3 }; // an array of pin numbers to which LEDs are attached
intpinCount = 6; // the number of pins (i.e. the length of the array)
void setup() {
// the array elements are numbered from 0 to (pinCount – 1).
// use a for loop to initialize each pin as an output:
for (intthisPin = 0; thisPin<pinCount; thisPin++) {
pinMode(ledPins[thisPin], OUTPUT);
}
}
void loop() {
// loop from the lowest pin to the highest:
for (intthisPin = 0; thisPin<pinCount; thisPin++) {
// turn the pin on:
digitalWrite(ledPins[thisPin], HIGH);
delay(timer);
// turn the pin off:
digitalWrite(ledPins[thisPin], LOW);
}
// loop from the highest pin to the lowest:
for (intthisPin = pinCount – 1; thisPin>= 0; thisPin––) {
// turn the pin on:
digitalWrite(ledPins[thisPin], HIGH);
delay(timer);
// turn the pin off:
digitalWrite(ledPins[thisPin], LOW);
}
} 24
```

முடிவு

ஆர்டியுனோ யுனொப் பலகையினைக் கொண்டு LED–க்களை தொடர்ச்சியான முறையில் இணைத்து, செயல்படுத்தும் முறையை அறிந்து கொண்டேன்.

XII EE_Tamil Version Practical.indd 343 1/18/2020 1:02:01 PM