```
$amps = [
    'Marshall' => 'EL34',
    'Fender' => '6V6'
];

if (array_key_exists('Marshall', $amps)) {
    print "Big bottle amps FTW!" . PHP_EOL;
}

Output:
Big bottle amps FTW!
```

array_key_exists() confirms that the key Marshall is present in $amps and returns true, if the key wasn't found it would return false.

Similar results can be obtained with the built-in isset() function, which will accept a wide variety of data types and return true if they exist and have a non-null value:

```
$amps = [
    'Marshall' => 'EL34',
    'Fender' => '',
    'Vox' => null,
];

print (isset($amps['Marshall'])) ? "Found a Marshall" . PHP_EOL : "";
print (isset($amps['Fender'])) ? "Found a Fender" . PHP_EOL : "";
print (isset($amps['Vox'])) ? "Found a Vox" . PHP_EOL : "";
print (isset($amps['Dumble'])) ? "Found a Dumble" . PHP_EOL : "";

Output:
Found a Marshall
Found a Fender
```

From the output we can see that isset() will return true if the array key is pointing to an empty string (it was also do this for bool false or int 0), but an explicit null returns false. A key that doesn't exist will of course also be false (who's even seen a Dumble amp anyway?!). Chapter 4, "Logic and Control," discusses which non-boolean values are usually considered true or false in more detail (and also explains the ternary logical operation – (CONDITION) ? VALUE_IF_TRUE : VALUE_IF_FALSE ; – used in this example.