Let's look at the explanation of the code.

Code	Explanation
import RPi.GPIO as GPIO	Imports the GPIO library for using the GPIO pins.
import time	Imports the time library for using the sleep function.
GPIO.setmode(GPIO.BCM)	
GPIO.setup(7, GPIO.IN)	Uses pin 7 on Raspberry Pi for PIR sensor detection.
print ("CTRL+C to exit")	Instructs the user to press [CTRL]+[C] to exit.
print ("Intruder Detector Ready")	Informs the user that the module is ready for operation.
while True:	Checks forever to see if there's an intruder.
if GPIO.input(7):	Checks if heat signature is detected by the PIR sensor.
print ("Motion Detected!")	If a heat signature is detected by the PIR sensor, it warns the user.
time.sleep(10)	Waits for 10 seconds

Now execute the Python script for intruder detection. On detecting an intruder, it will display a warning for the same.

Hook up a flashlight to the camera and you could catch that sneaky animal that's been prowling in your backyard.