

Or even better, why shut down your computer at all when you can suspend or hibernate it? Use these features generously as they will let you shut down and start up your computer nearly instantly.

Another thing you can do is turn on autologin for your account. Surely this is not advisable for everyone, however, those who are using their computer at home, in a single user environment, the boot process can be made just a little quicker if you don't have to type your password each time. Note that you do not need to remove your password entirely. Your password can still be used to lock your computer, during subsequent logins or while using "sudo", etc.

1. Use your pendrive as swap to emulate Windows ReadyBoost

Windows has a nice feature called ReadyBoost that allows your pendrive to be used as temporary swap space to boost the performance of your computer. Since pendrives have lower access times than hard disks, using your pendrive as swap can boost your performance. For this you will need to use a ReadyBoost-capable pendrive. Many pendrives available in the market today tout this support so you should be able to find out if you have one. While this will work with any pendrive, ReadyBoost capable pendrives work best.

There are two ways to do this. You can either use your entire pendrive as swap, or you can create a swap-file on your pendrive. We will assume you have mounted your pendrive at /media/disk

You might need to login as superuser or use sudo for these commands. First create a swap file using the "dd" command (if is input file, of is output file, bs is block size, count is block count):

```
dd if=/dev/zero of=/
media/disk/extraswap
bs=1M count=1024
```

This will create a 1024MB swap file on your pendrive.

Now you need to format this as swap:

```
mkswap /media/
disk/extraswap
```

Finally, we activate this swap-file to put it to use by typing:

```
swapon -p 32767 /
media/disk/extraswap
```

Adding "-p 32767" gives this swap file the highest possible priority ensuring that it is put to use.

If you wanted to make your entire pendrive a swap drive, you can skip the first step, and simply use mkswap /dev/sdx1 where sdx1 is your pendrive device. In the last step you can again use this device instead of a file. Remember, this will destroy your data! It is better to create a large file instead, as the performance drop for not using the drive is not huge.



"System" Menu > Administration > Login Screen

To turn the pendrive swap off in order to unplug the drive, use:

```
swapoff /media/
disk/extraswap
```

0. Compile your own Linux kernel

Sooner or later you'll want to do the mother of all optimisations, a custom kernel compiled with your love. To get you started with this we have an entire article dedicated to the Linux kernel, and how to compile your own version. Turn over to page 135 in this issue for the article.

Now with your lean and mean Ubuntu 10.10 install you can boost your work output, as long as you don't let your Facebook addiction stand in the way. 



**TOP GUN
TECHNOLOGIES**
Best of the Best

THE BEST NETWORK & SECURITY LABS IN INDIA



**Others Promise.
We Deliver !**

Integrated Program for Fresh Graduates

**CCIE - Security
CCIE - R & S**

Special Offer

**CCNA Rs. 5,000/-
CCNP Rs.30,000/-
CCSP Rs.30,000/-**

Loans through  HDFC BANK

Congrats to our Latest CCIEs

Mr. Jitendra Siyag	CCIE Security # 27022
Mr. Mahesh A	CCIE # 26985 (v4.0)
Mr. Mohammad Saud Reyaz	CCIE # 26899 (v4.0)
Mr. Suresh Kumar K.	CCIE Security # 26621
Mr. Solomon S	CCIE Security # 26508
Mr. Ashis Kumar J	CCIE Security # 26299
Mr. Louis Kallith	CCIE # 26271 (v4.0)
Mr. Akram El-Samiri	CCIE # 26163 (v4.0)
Mr. Divin Mathew John	CCIE # 25905 (v4.0)
Mr. Renash Chandran	CCIE # 25904 (v4.0)

Courses Offered:

CCIE, CCNP, CCNA, CCSP, CCIP, CWNA, CWNP, CWSP, CCSA, CCSE, CISSP

Well Qualified Instructors

AJAY PANDEY

B.E, MS (USA), CCIE # 14792, (Security / R&S), CISSP, CISA, CISM, CCSE, MCSE, ASAP.

SUNNY SHARMA

BCS, CCIE # 24088 (Security), CCSP, CCNP, CWNA, CEH, MCSE.

Lab Equipped with :

91 Cisco Routers (2811, 2621 XM, 3600, 2600, 2500, 1700, 700), 24 Cisco Catalyst Switches (5000, 3750, 3560, 3550, 3000, 2950, 2900), Frame - Relay / ISDN, 8 Firewalls : SonicWall, Watch guard, Cisco PIX 515 E (UR), ASA 5510, PIX 501, 3005 VPN concentrator, 4210 IPS sensor, Nokia IP 330, Check Point, CiscoWAP/ NICs, Cisco Call Manager MCS 7825

Local Accomodation Available

We have Graduated over 67 CCIEs.

BANGALORE

Visit our Website :

www.topguntechnologies.com

info@topguntechnologies.com

SMS 080- 65616600

080-23528500 / 41277710

If you find a better Institute to do any of these courses, Join it !