

really need to update your antivirus right now! Remove the virus using the Kill CIH tool. Download it from: http://www.symantec.com/avcenter/kill_cih.html

The tool actually disables the virus from the memory. After CIH is "killed", update your antivirus definitions and run a full system scan. The infected files will get removed only after this.

The flickering problem with Outlook Express or MS Word may not be directly caused by this virus. In any case, update your antivirus and try again!



Cannot Format Hard Disk

Q I have a 40 GB Seagate hard disk with Windows XP, which has stopped working. A hard disk utility recognises the hard disk and shows the partitions. I can delete partitions or create new ones, but when the system restarts, the previous partitions reappear. I have done a low-level format, but the problem persists. What should I do?

Prashanth Siddapur
Bangalore

A It seems the Master Boot Record (MBR) area of your hard drive has a bad sector. To tackle this problem, download Disk Manager 5. Use the Advance option to format your hard drive. Instead of size, use cylinder numbers to create a partition. Leave alone the first eight to ten cylinders and start from cylinder number 11 or 12 to create partitions. If this doesn't work either, you'll need to replace the hard disk. If you continue using the hard disk, take regular backups of all your data.

Backing Up E-mail

Q My hard disk has developed bad sectors. Before replacing them, I want to take a backup of my Outlook Express files. Please help me out with all the steps required to do it.

R. Siva Kumar

A First, you need to back up both your e-mails (.DBX) and address book (.WAB). Follow these steps:

1 To back up your e-mail Outlook Express, go to Tools > Options > Maintenance. Under the Maintenance tab, locate the Store Folder button and click on it

2 This will open a dialog box showing the path where your .DBX files are stored

3 Copy this path and close the Tools window. Click Start > Run, paste the path and press Enter

4 The new window that opens will show

Can't Open PageMaker Files


Q Without any apparent reason, some PageMaker 7.0 files on my D: drive were corrupted. When I try to open these files, I get this message: "Cannot open file format not supported...". How do I solve this problem?

greyblue86@yahoo.co.in

A Create a copy of any of those corrupt files, and open them using File > Open in PageMaker itself, instead of double-clicking the files.

Secondly, PageMaker stores information like plug-ins, features, etc. in a preferences file called PM70.cnf. This file is located in the Program Files\Adobe\PageMaker 7.0\Rsrc\Usenglsh folder. Exit PageMaker and rename this preference file. Now, restart PageMaker 7.0 and it will re-create the same.

The file will not open if the graphic link is corrupt. The graphic link actually links you to the graphic stored on the hard drive. To work around this problem, move the graphic to some other location on the hard drive. Now, try opening the copy. If it opens correctly, use the Link Manager in PageMaker to restore the graphic link from the new location where graphic was later stored. You can also try Symantec Norton utilities for restoring corrupt files. Find all this at <http://www.symantec.com/sabu/sysworks/basic/>



Obtain the path to your e-mail folder from this dialog box

multiple .DBX files. Copy all of them

2 Create a new folder and name it appropriately, such as "Mail Backup." Here, paste all the .DBX files, then close the folder

To back up your mail:

1 In Outlook

Express, go to File > Export > Address Book

2 In the window that opens, click the Comma Separated Values check box, and then select Export

3 Click Browse and locate the Mail Backup folder made earlier (while backing up your e-mail). Save your address book as an Address Book Backup with an appropriate name, then click Next

4 In the Window that opens, check the fields that you think need to be backed up. Click OK and then click Close.

Computer Won't Hibernate

Q I have Windows XP Professional running on an Intel Pentium 4 2.4 GHz processor. After a re-install, I face several problems. Whenever I shut the PC down, the system restarts automatically without any error messages. In the shutdown dialog box, the Standby option is disabled. And in the Power Options on the Control Panel, the Hibernation tab is missing!

Also, when I open the registry editor, it stops responding. What could be the problem? I don't want to reformat my hard disk.

Swarup

Need info on
Hard Disc Drives



Call 1600 33 11 04

Seagate

