

```

#include "stdafx.h"
#include "pxcsession.h"
#include "pxcsmartptr.h"
int _tmain(int argc, _TCHAR* argv[]) {
    PXCSmartPtr<PXCSession> session;
    PXCSession_Create(&session);
    for (int i=0;;i++) {
        PXCSession::ImplDesc desc;
        pxcStatus sts=session->QueryImpl(0,i,&desc);
        if (sts<PXC_STATUS_NO_ERROR) break;
        wprintf(L"Module: %s, iuid=0x%x\n",desc.friendlyName,desc.iuid);
    }
    return 0;
}

```

The SDK Hello-World Application

meet your application needs, you can recompile the libpxc or the libpxcutils libraries, whose build script is under \$(PCSDK_DIR)/src/libpxc and \$(PCSDK_DIR)/sample/common respectively.

A SIMPLE SDK APPLICATION

Example 1 is a simple hello-world type of application that prints out all preinstalled SDK modules. The application will print out the following information:

- Module: DepthSense 325 Audio/Video Capture, iuid=0x32444b53
- Module: Face Analysis (Intel), iuid=0x434c4946
- Module: Hand/Finger Tracking & Gesture Recognition, iuid=0x49434b53
- Module: Video Capture (Media Foundation), iuid=0x464d5f43
- Module: Audio Capture (Media Foundation), iuid=0x41464d43 ■

