



verification key that is sent as a text message to your phone.

Once you're verified click on 'Create a live event' > *Give it a name* > Schedule the date and time > Add Tags > Choose access type (Public, Unlisted, Private) > Select Custom (more encoding options) under Type > Create Event.



Tweak YouTube's Ingestion settings

In the Ingestion Settings tab, select a thumbnail for your live stream > choose 'Basic Ingestion' > Select a bit rate according your requirement considering your upload speed > Choose 'Other Encoder' and select from the more options that appear below.

Copy the unique 'stream name' that you'll see and go back to OBS. In OBS, you need to change the Broadcast settings. To do this, click on Settings > Broadcast Settings > Choose 'Live Stream' as Mode > Choose 'YouTube' as Streaming Service > Choose 'Primary YouTube ingest server' as Server > Paste the stream name in the Play Path/Stream Key field > Click 'OK'.



Control your stream from YouTube's Live Control Room

Click on the Live Control Room tab and you'll see 'No Data' because nothing is streaming at the moment. Go to OBS, start streaming, and then return to YouTube and wait until you see Stream Status as 'Good'. Click on 'Preview' followed by the Play button of the YouTube player. You'll now see the preview of what you're streaming. If you're all set, click on 'Start



Copy the Stream Name to the Stream Key field in OBS

Streaming' and your stream will be live.

CABLE MANAGEMENT

Pay attention to the cables inside your PC. Here's how



Routing mobo cable

The first cable that you should route is the motherboard cable which is the thickest and ugliest among all the other cables. Take the cable > pass it through the lowest routing hole next to your power supply > carry it straight up through the back of the motherboard tray till right where the 24-pin port exists on your motherboard > pass it through the routing area next to the port > connect it in. Make sure to not make any twists or loops on the motherboard cable because that would become very



This is how the back of the case should look like.

thick and wouldn't let you close the side panel.



Route CPU cable

Pick out the CPU power cable > pass it through the hole which you used for the motherboard cable > prop-up the cable at the back > align it next to the CPU cutout area > bring

it out to the other side of the case through the routing hole near the 8-pin CPU power port > connect it to the port. This way of routing the CPU power cable ensures that it stays out of the way of the other cables inside the case and is easily distinguishable.



Route GPU cable

Take a look at the PCIe x16 slot on your motherboard and keeping that in mind > connect the PCIe 6-pin or 8-pin power connector to the PSU > pass cable through routing holes near the PSU > don't overlap them over the motherboard power cable and use the routing hole to pass the cable through to near the area where the GPU will be installed. Install the GPU at the very end of the entire process as this gives you more room to work around.



Routing SATA power and SATA data cables properly

Take the SATA power cables > connect

them to the PSU > group them together > pass them through the routing holes > align the cables at the back of the tray taking them away from the cluster of PCIe and motherboard cables towards the drive cages > connect them to the drives. As for SATA data cables, it's best to group them together one above the other since they're flat and pass them through the routing holes and connect them to the drives. In case of excess cable length, fold the cables and tuck them behind the drive cages away from sight.



Fan, case cable etiquette

If you have installed the fans in the right places, group their



For some inspiration

cables according to their placement for example: group cables of the front fans together and the rear or top fans together. If the cables are long enough to reach the motherboard tray, approach through the shortest path and connect them to the ports through the back of the tray. In case the cables are short, you'll have to use the fan adapter which is usually included with the fans and connect it to the molex power cable of the PSU. Connect the cables of your PC case after this, follow the same grouping process and connect them to the ports on the motherboard after you've passed them through a routing hole right next to the front panel connector ports.