



A custom Arduino™ board

Any hardware designed as well as any piece of Arduino™ code written for Arduino™ Uno and Arduino™ Leonardo can be used as is on the Arduino™ Yún, Arduino™ Due and Arduino™ Mega 2560. But code and hardware designed for Arduino™ Yún, Arduino™ Due and Arduino™ Mega 2560 might

need some modification on the Arduino™ Uno and Arduino™ Leonardo.

Also, since the Arduino™ Yún also employs Linux as an environment, the Linux code written using the bridge for Yún cannot be used on any other board.

## Software

The Arduino™ IDE (Integrated Development Environment) is software that's used to write the code which is run on the microcontroller of the Arduino™ board. Here's how to install it on popular platforms:

### Windows

1. Download the Arduino™ IDE installation file (Arduino-1.0.6-windows.exe) from <http://dgit.in/ardsoft>.
  - a. For the Arduino™ Yún and Arduino™ Due boards, you'll need the Arduino 1.5.8 version available at <http://Arduino.cc/en/Main/Software>.
2. Open the downloaded file and install it.

### Linux

1. Ubuntu/Debian users can install the IDE by opening the terminal and giving the following command:
  - `sudo apt-get install Arduino`
2. Others can download the corresponding IDE from <http://dgit.in/ardsoft> depending on whether you're using the 64 or 32 bit version of the OS.
3. Extract the downloaded archive using the following command:
  - `tar zxvf <filename>.tgz`
4. Open the extracted folder in the terminal.