

<code>Serial.println("Scanning available networks...");</code>	
<code>listNetworks();</code>	List all available Wi-Fi networks by calling the 'listNetworks()' function defined below
<code>Serial.print("Enter name of network: ");</code>	
<code>readSerial(ssid);</code>	Call a function named 'readSerial()' to read SSID (name) of network entered by user and store in variable 'ssid'
<code>Serial.print("Enter password: ");</code>	
<code>readSerial(password);</code>	Call function 'readSerial()' to read password entered by user and store in variable 'pass'
<code>Serial.println("Attempting to connect ");</code>	
<code>status = WiFi.begin(ssid, password);</code>	Connect to Wi-Fi network with name 'ssid' and password 'pass'
<code>if(status != WL_CONNECTED) {</code>	Check if you're connected to the Wi-Fi network connection
<code>Serial.println("Couldn't get a wifi connection");</code>	
<code>while(true);</code>	Stop further execution since you're not connected to any Wi-Fi network
<code>}</code>	
<code>else {</code>	
<code>Serial.println("Connected to network");</code>	Display success message
<code>}</code>	
<code>}</code>	
<code>void loop() {</code>	
<code>// do nothing</code>	
<code>}</code>	

FUNCTION TO LIST AVAILABLE NETWORKS

<code>void listNetworks() {</code>	Function to list all available Wi-Fi networks
<code>Serial.println("Available Networks: ");</code>	
<code>byte numSsid = WiFi.scanNetworks();</code>	Scan for available networks and store count in variable 'numSsid'
<code>Serial.print("number of available networks:");</code>	
<code>Serial.println(numSsid);</code>	
<code>for (int thisNet = 0; thisNet < numSsid; thisNet++) {</code>	For every network found, print following data
<code>Serial.print(thisNet);</code>	Print count of network
<code>Serial.print(" ");</code>	
<code>Serial.print(WiFi.SSID(thisNet));</code>	Print SSID (name) of the Wi-Fi network.