

```

• from twisted.internet import reactor

• import RPi.GPIO as GPIO
• GPIO.setmode(GPIO.BCM)
• GPIO.setmode(18, GPIO.OUT)

• class lampAPI(Resource):
•     def render_GET(self, request):
•         if 'bulb_status' in request.args:
•             if request.args['bulb_status'][0]
== "off":
•                 GPIO.output(18, False)
•                 return "Bulb has been
turned OFF"
•             if request.args['bulb_status'][0]
== "on":
•                 GPIO.output(18, True)
•                 return "Bulb has been
turned ON"

• root = Resource()
• root.putChild("interface", lampAPI())
• factory = Site(root)
• reactor.listenTCP(80, factory)
• reactor.run()

```

Now press [Ctrl] + [X] together, then [Y] and then press the [Enter] key to save the file.

Code	Explanation
from twisted.web.server import Site from twisted.web.resource import Resource from twisted.internet import reactor	Imports the Twisted Python server libraries.
import RPi.GPIO as GPIO GPIO.setmode(GPIO.BCM) GPIO.setmode(18, GPIO.OUT)	Imports the GPIO libraries which are like the code for LED blinking.