

<code>class lampAPI(Resource):</code>	Define a new class
<code>def render_GET(self, request):</code>	Define render_GET function
<code>if 'bulb_status' in request.args:</code>	Checks if a variable 'bulb_status' exists in the received URL.
<code>if request.args['bulb_status'][0] == "off":</code>	Checks if the parameter for the 'bulb_status' variable has been set to 'off'.
<code>GPIO.output(18, False)</code>	Switches OFF the light if the user sends the 'off' parameter.
<code>return "Bulb has been turned OFF"</code>	Informs the user that the bulb has been switched OFF.
<code>if request.args['bulb_status'][0] == "on":</code>	Checks if the parameter for the 'bulb_status' variable has been set to 'on'
<code>GPIO.output(18, True)</code>	Switches ON the light if the user sends the 'on' parameter.
<code>return "Bulb has been turned ON"</code>	Informs the user that the bulb has been switched ON.
<code>root = File("myserver")</code>	Specifies the server files storage folder as 'myserver'.
<code>root.putChild("pi_auto", lampAPI())</code>	Creates a child of resource to handle requests.
<code>serve = Site(root)</code>	Initialises the 'twisted' object.
<code>reactor.listenTCP(80, serve)</code>	Sets the server to handle request on port 80.
<code>reactor.run()</code>	Keeps listening on port 80 forever until turned OFF manually.

To turn ON and turn OFF, simply type the following URL in the browser.

To turn ON the light:

http://<ip-address>/pi_auto?bulb_status=on

To turn OFF the light:

http://<ip-address>/pi_auto?bulb_status=off

Now type the following command in the terminal:

- `mkdir myserver`