

This will create a directory with the name 'myserver' as specified in the program with 'res_var = File("myserver")'. Now, in terminal, type the following to change the current directory to the newly created folder 'myserver':

- `cd myserver`

In the newly created 'myserver' directory, create an HTML file that will be accessed by the user to turn ON or OFF the lights by merely entering:

- `nano index.html`

Now type the following code in the text editor to create a webpage:

- `<!DOCTYPE HTML>`
- `<html>`
- `<head>`
- `<title>Light control using Raspberry Pi</title>`
- `</head>`
- `<body>`
- `<h1> Bulb control </h1> <br>`
- `<a href="http://<ip-address>/pi_auto?bulb_status=on">`
- `<h2> Turn ON </h2> </a> <a href="http://<ip-address>/pi_`
- `auto?bulb_status=off"> <h2> Turn OFF </h2> </a>`
- `</body>`
- `</html>`

Now press the [Ctrl] + [X] keys together, then the [Y] key and then press [Enter] to save the file.

Now enter the following command to run the light control Python script:

```
python basic_switch.py
```

Bulb control

[Turn On](#)

[Turn Off](#)

After writing this program you can access the webpage using the IP address of the Raspberry Pi in the browser (Chrome/Firefox) as:

<http://<ip-address>/>

This will open a webpage with the option to turn ON and turn OFF the light as shown in the screenshot.