

What more, you can extend the above code to take a picture of the intruder, using the `fswebcam` or `picam` utility mentioned in the previous chapter. All you need to do is change the 'while' loop, after you've connected the webcam and installed the `fswebcam` package (if you're using a regular camera) or the `picam` package (if you're using the official Raspberry Pi camera).

The Python code for the same to take a photo of the intruder will be as follows:

```
• import RPi.GPIO as GPIO
• import time
• GPIO.setmode(GPIO.BCM)
• GPIO.setup(7, GPIO.IN)
• print ("CTRL+C to exit")
• print ("Intruder Detector Ready")
• while True:
•     if GPIO.input(7):
•         print ("Motion Detected!")
•         filename=$(date -u
+ "%d%m%Y_%H%M%S").jpg
•         fswebcam -d /dev/video0 -r
640x480 $filename
•         time.sleep(10)
```

Thus, using the above code, we'll be able to take a photo of the intruder along with the time of the photo capture.

Code	Explanation
<code>filename=\$(date -u + "%d%m%Y_%H%M%S").jpg</code>	Creates the name of the image file using the date command in the format 'Date-month-year_hour-minutes-seconds'
<code>fswebcam -r 1024x768 \$filename</code>	Saves the image with the given file name.

What we saw above are some basic projects that can help you get started. There are many more home automation projects that can be created with the Raspberry Pi.

Stream your home temperature

This is a simple project that will only stream the current temperature of your home using the Raspberry Pi.