

In the text editor that appears in the terminal, enter the following piece of code:

```

• from twisted.web.server import Site
• from twisted.web.resource import Resource
• from twisted.internet import reactor
•
• import RPi.GPIO as GPIO
• GPIO.setmode(GPIO.BCM)
• GPIO.setmode(18, GPIO.OUT)
•
• class lampAPI(Resource):
•     def render_GET(self, request):
•         if 'motor_status' in request.args:
•             if request.args['motor_status']
[0] == "off":
•                 GPIO.output(18, False)
•                 return "Motor / Solenoid
has been turned OFF"
•                 if request.args['motor_status']
[0] == "on":
•                 GPIO.output(18, True)
•                 return "Motor / Solenoid
has been turned ON"
•
• root = Resource()
• root.putChild("pi_auto", lampAPI())
• serve = Site(root)
• reactor.listenTCP(80, serve)
• reactor.run()

```

Now press [Ctrl] + [X] together, then [Y] and then press [Enter] to save the file.

Now let's create the webpage that will be used to control the motor / solenoid. Type the following command in the terminal:

```
• mkdir myserver
```

This will create a directory with the name 'myserver' as specified in the program with 'res_var = File("myserver")'. Next, in the terminal, type the following command to change the current directory to the newly created