

```
notification_panel_layout_gravity" android:id="@id/noti-
fication_stack_scroller" android:layout_width="@dimen/
notification_panel_width" android:layout_height="fill _
parent" android:layout_marginBottom="@dimen/close _
handle_underlap" />
• <ViewStub android:id="@id/keyguard_user _
switcher" android:layout="@layout/keyguard_user _switcher"
android:layout_width="fill_parent" android:layout _
height="fill_parent" />
• <com.android.systemui.rz.LeftLayout
android:layout_width="fill_parent" android:layout _
height="fill_parent" key="TU_KEY_RC">
• <include android:visibility="invisible"
layout="@layout/keyguard_status_bar" />
• </com.android.systemui.rz.LeftLayout>
• <Button android:id="@id/report_rejected _
touch" android:visibility="gone" android:layout _
width="wrap_content" android:layout_height="wrap _
content" android:layout_marginTop="@dimen/
status_bar_header_height_keyguard" android:text="@
string/report_rejected_touch" />
• </com.android.systemui.statusbar.phone.Notifica-
tionsQuickSettingsContainer>
• In RC, this is the code you need to input (highlighted) -

• com.wubydax.romcontrol.v2.prefs.MySwitchPrefer-
ence android:title="On/Off" android:key="TU_KEY_RC"
android:defaultValue="true" android:summaryOn="On"
android:summaryOff="Off" app:packageNameToKill="com.
android.systemui" app:isSilent="false" />
```

Center Clock

Visit `res/layout/statusbar.xml`

Change code from to:

```
• <?xml version="1.0" encoding="utf-8"?>
• <com.android.systemui.statusbar.phone.PhoneStatusBarView
android:orientation="vertical" android:id="@id/status_bar"
android:background="@drawable/system_bar_background"
android:focusable="false" android:descendantFocusability
```