

terminal or log off from the main menu and make way to the Bash prompt. Once in the Bash prompt, enter `sudo halt -h` and wait for your device to turn off. Check if all the LEDs have gone off and once they do, wait for 15-20 seconds more to make sure that the SD card has done its work correctly. You can now remove your Raspberry Pi easily without the fear of wasting your SD card.

Power

A 5V micro USB powers the Raspberry Pi. The first model came with a suggested power capacity of 700mA and has since kept fluctuating as per models. The Raspberry Pi Model B requires a power of 1.2A to operate, whereas the Raspberry Pi 2 needs 1.8A. The successor, Raspberry Pi 3, requires a power draw of 2.5A, and the latest model has a requirement of 3.0A. The smaller siblings Raspberry Pi Zero series need you to allocate 1.2A power to them.

On the other hand, Raspberry Pis can support a maximum of 500mA to 1.2A supply for the USB devices connected to it. Use a power-hub if you think that you need more power. On the Raspberry Pi 3 Model A+ and the Zero series, the power output is limited by PSU, boards, and connector ratings only. The power requirements increase as you increase the workload on your device.

Remember that the GPIO pins can draw up to 50mA without any issues and an individual GPIO pin can draw up to 16mA. The keyboard and mice can take up as much as 1000mA and as low as 100mA.

The camera module and the HDMI port uses 250mA and 50mA power, respectively. To keep all of it secure, the Raspberry Pi Foundation suggests a good quality 2.5A power supply unit. It should be enough for anything and everything you throw at your device.

SD card slot

Initially, Raspberry Pi Model A and Model B incorporated full-size SD cards slots for their devices. Since then, they have switched to microSD for all the later additions to its portfolio.

The OS is on the SD card, and hence you must be careful while engaging and disengaging it from the power source. Raspberry Pi Foundation suggests a minimum of 8GB card for you to operate safely.

Various users have tried up to 128 GB cards, and all of them seem to work nicely without any issues.