

from Linux, no Linux user will feel lost inside this system, and will be able to pick it up very quickly.

FreeBSD has no major graphical installation, and processes can be carried out in a straightforward manner. It is identical to installing a server-based Linux system vision system.

USB Storage devices

Various external storage devices such as USB drives, hard drives, and CD/DVD burners use the USB interface. FreeBSD offers support for the first two generations of USB devices.

Note: USB 3.0 devices are incompatible with many hardware, such as Haswell chipsets, etc. If FreeBSD boots with the message ‘failed with error 19’, then disable the xHCI/USB 3 setting in the BIOS system.

The USB support for the storage devices can be channelled into the ‘GENERIC’ kernel. In order to include this support in the kernel, make sure the following lines of code are in the configuration of the kernel file:

- `device scbus # SCSI bus (required for ATA/SCSI)`
- `device da # Direct Access (disks)`
- `device pass # Passthrough device (direct ATA/SCSI access)`
- `device uhci # provides USB 1.x support`
- `device ohci # provides USB 1.x support`
- `device ehci # provides USB 2.0 support`
- `device xhci # provides USB 3.0 support`
- `device usb # USB Bus (required)`
- `device umass # Disks/Mass storage - Requires scbus and da`
- `device cd # needed for CD and DVD burners`



USB storage device