

- BSSID of the network.

Just like in the case of WEP, we will be using airodump-ng to display the networks in range. Here are the steps-

- Set your wireless interface in monitor mode-

- `airmon-ng start wlan0`

- Use airodump-ng. It will show all the networks around you. It tells which of them use WPA. You'll have to assume they have WPS, and then move to the next steps.

- `airodump-ng mon0`

BSSID of the network - We need a BSSID column in the result that we will get. Take a note of the BSSID of the network that we want to hack.

Reaver

We will use Reaver to get the password of the given network. Reaver makes hacking very easy. We use the command :

- `reaver -i mon0 -b XX:XX:XX:XX:XX:XX`

OR

- `reaver -i wlan0mon -b XX:XX:XX:XX:XX:XX`

i - interface used. It was created using airmon-ng, and the name depends on the version of Kali Linux used.

b - species the BSSID of the network that was noted earlier.

This is all that is needed by Reaver to start. Reaver does come with many advanced options.

The most important of these is the -vv option, which increases the verbosity. Verbosity displays what is going on in the background and can provide new insights into how it functions, especially to a newbie. This option also helps in the troubleshooting process. So the final command should be-

- `reaver -i mon0 -b XX:XX:XX:XX:XX:XX -vv`

OR

- `reaver -i wlan0mon -b XX:XX:XX:XX:XX:XX -vv`