


unmount the motherboard from the screws. You need not necessarily remove the processor and the RAM module before doing this; however, it is recommended that you remove the RAM modules from their slots before proceeding to remove the motherboard. If you bought a new case and are installing a motherboard in it, the steps so far do not apply.

4. Now, get the new motherboard out of the anti-static bag, and try fitting it into the case. Check for the studs and screw bases on the motherboard and see if the motherboard fits properly on top of them, and that the screw-holes on the motherboard coincide with the screw base and studs. If some of them are not coinciding, mark that particular screw base or stud and remove it. If there is a new one required to be installed, install one from the packet of screws accompanying the motherboard. You will have also received a back panel case with the motherboard that fits on to the back of the tower case. This is shown in the image below. This back panel is important since it is made in such a



Install the screwholders to place the motherboard on. Place the motherboard on the installed screwholders and place the screws properly