

RAM, and it is supposed to load with CONFIG.SYS. The error is either a result of a corrupt HIMEM.SYS file, or physical issues such as a RAM module not meeting the system board specifications.

Solution: Assuming that the file is actually corrupt, let's overwrite it with a new file. Boot the system with a Win 9x



Only one Notch

DDR RAM Module

DDR RAM has only one notch and it is not centrally located

startup disk. If the system boots properly, then it is likely that Himem.sys is corrupt or missing, or it hasn't been configured properly in CONFIG.SYS. At the prompt (A:\>) type in "**copy himem.sys C:\WINDOWS**" and press [Enter]. If you encounter the problem on rebooting the system, then edit CONFIG.SYS and make sure that it contains the line

DEVICE=C:\WINDOWS\HIMEM.SYS

Save the edited file and reboot the system. You will have to consult a technician or replace the module(s) if the problem persists.

► **Problem:** New RAM Module Doesn't Work On A Branded PC

You purchased a new RAM module and installed it in addition to an existing module on a branded PC. The new module is not detected by the computer.

Cause: Some branded PC manufacturers customise computer peripherals to deliver better performance. Due to this customisation or proprietary peripherals, a user is unable to buy and install peripherals available in the market. If you do, mismatch errors are encountered.

Solution: Upgrading of the RAM must be done through the dealer of your branded machine. Call their customer care centre for assistance.

► **Problem:** Problem Booting A RIMM-Based Machine

A RIMM-based machine fails to boot when a few RIMM slots are left open.