

AGP Slot Specifications

Motherboard Type	Slot Type	Details
AGP 3.3V	3.3 V keyed	Supports only 3.3 V signalling. Available speeds are 1x, 2x.
AGP 1.5V	1.5 V keyed	Supports only 1.5V signalling. Available speeds are 1x, 2x, 4x.
Universal AGP Motherboard	Universal	Supports both 3.3 V and 1.5 V signalling. Available speeds are 1x, 2x at 3.3 V and 1x, 2x, 4x at 1.5 V.
AGP 3.0	1.5 V keyed	Supports only 0.8 V signalling. Additional electrical ID to prevent 1.5 V operation. Available speeds are 4x, 8x.
Universal 1.5V AGP 3.0 Motherboard	1.5 V keyed	Supports 1.5 V and 0.8 V signalling. Available speeds are 1x, 2x, 4x at 1.5 V and 4x, 8x at 0.8 V.
Universal AGP 3.0 Motherboard	Universal	Supports 3.3 V, 1.5 V, and 0.8 V signalling. Available speeds are 1x, 2x at 3.3 V; 1x, 2x, 4x at 1.5 V; and 4x, 8x at 0.8 V.

For the AGP card to work with the motherboard both the slot type and the signaling voltage has to match. Verify the compatibility between your AGP card and motherboard using the table on the next page (*AGP Card And Motherboard Compatibility*). Note that for all practical purposes, none of the manufacturers make cards and motherboards with just AGP 3.0 (greyed out in the chart).

Stabilising the AGP port: Adjusting the AGP speed multiplier and Fast Writes can stabilise your AGP port. Typically, both the motherboard and the AGP port are initialised to the highest speed