

- ▶ Go to the Project options in Qt Creator: Tools > Options > Projects > MeeGo Device Configurations.
- ▶ Click the “Add” button to create an emulator configuration, which will use QEMU or hardware device.
- ▶ To use QEMU, set the following values:
 - Device type: MeeGo emulator
 - Authentication type: Password
 - hostname: localhost (or 127.0.0.1)
 - SSH port: 6666
 - Username: root
 - Password: meego
- ▶ Click “Projects” again on the left side.
- ▶ Select “Run” in the MeeGo Build/Run box at the top. Make sure that the “Device configuration” is set to “MeeGo Emulator”. This will ensure that QEMU is started when you run your application.
- ▶ You can now launch the QEMU MeeGo emulator. Click the “Start MeeGo emulator” icon near the bottom left corner of Qt Creator (circled in red in the screenshot below).

Note: You can also start the Qemu from MADDE terminal. For that you need to go to Start > Programs > MeeGoSDK > MADDE Terminal. In the terminal type:

- `mad list`
- to see the runtime and target names, and then type:
- `mad remote -r <runtime> poweron`

Launch the QEMU MeeGo emulator by clicking on the Start MeeGo emulator icon on the bottom right of the screen

