

- ▶ the sample code illustrating the use of SDK
- ▶ It also provides a debugger, which can be installed with a few extra steps. After installation, there will be a new menu folder under “Start” > “All Programs”, by the name of “Intel AppUpSM Software Development”. This is the folder that contains direct access to some of the bullet items above.

Ensure correct settings

It is useful to make sure all compile and runtime settings are included correctly. One of the easiest ways has been described below:

- ▶ Start Qt Creator: “Start” > “All Programs” “MeeGo 1.1 SDK” > “Qt Creator”
- ▶ Make sure you start Qt Creator as Administrator, which is an option under the left mouse menu of “Qt Creator”.
- ▶ From Qt Creator, go under “File” > “Open File or Project...”
- ▶ Choose from
“C:/Program Files/Intel/IntelAppUpSDKMeeGo/Cpp/Samples/cpp/AdpSimpleSample/”
and open AdpSimpleSample.pro.
- ▶ If MeeGo SDK or Intel AppUpSM SDK Suite were both installed correctly, you will see a green phone-line button at the lower left hand corner of Qt Creator, below the two green arrows. The phone-line button should also not be greyed-out.
- ▶ An example of what it would look like if the SDK was not installed properly:
- ▶ If you get the version without the emulator button on the lower left corner or it is greyed-out, make sure:
 - a. Qemu is started properly (the step in MeeGo SDK that says “net start kqemu”). Make sure the command prompt is started as “Administrator”, which will make Qemu run as “Administrator”.
 - b. Make sure QtCreator is starting in “Administrator” mode.
- ▶ Next, go to the “Projects” tab to make sure the runtime and build configuration are set properly.
 - a. For example, to build a netbook application, the build configuration should point to “meego-netbook”
- ▶ The runtime emulator should also be pointing to the MeeGo emulator that was set up under MeeGo SDK