

CHDK is a non-destructive and a temporary firmware upgrade, so you can always remove it. It leaves your stock firmware untouched. After you delete the software from your memory card, the camera functions normally. So it does not void your camera's warranty, but who knows! We're not giving any legal opinion. Log on to <http://dgit.in/MskIAf> to get a list of camera models and firmware versions that are currently supported by CHDK. Check your camera's model and firmware version before you go on installing it(<http://dgit.in/KSIa9g>). A different version of CHDK works for different firmware versions even of the same camera model.

Download and install CHDK

CHDK has two builds: 1.0.0 and 1.1.0. The 1.0.0 build has a more stable code, whereas the 1.1.0 build is called a development trunk where new code is introduced. Download the correct build for your camera from <http://dgit.in/NQj8NA>. Installing it involves copying the required CHDK program files to your camera's memory card. It gets loaded into your camera's memory upon boot up (either manually or automatically). For loading it manually every time you turn on your camera, use the Firmware Update method where you use the camera's built-in 'Firmware Update' menu item to load CHDK. If you want it to load automatically when you turn on your camera, use the Bootable SD card method. Follow the instructions in the following link and then lock your card by sliding the LOCK switch on its side. You will see the CHDK logo flash on the screen when you turn on the camera.



Uninstalling CHDK from the file system requires you to delete those files from the memory card. Since CHDK is loaded onto the RAM, no permanent changes are made to your ROM or filesystem. For more details read on <http://dgit.in/Msn6Ha>.

What new features CHDK brings to your camera?

CHDK is a continuously evolving software, and developers from all around the world are continuously working towards improvising its features for different camera models. Some of the enhancements that it brings to your simple cameras are: