

4. Dell's Chromium build [<http://tinyurl.com/yay5k7g>] - 313MB - No longer updated but compatible with Dell Mini and other models of Dell's hardware that may not be supported by other OS builds.



The Vanilla Chrome build promises to be as close to original as possible

Once all these files and software's have been obtained you are ready to begin the process of setting up Chrome OS or Chromium on to your system.

We shall be using the Hexxeh Vanilla Chrome build 4028 for the purposes of this guide but any of the suggested versions would work just as well. It's also important to note that Chrome OS and Chromium OS are not like traditional operating systems in most ways. The default and most popular way of using them is through a bootable USB or SD Cards. In case of true dual booting you need to have two separate hard disks since Chromium formats the entire hard drive with no option of making a partition before the formatting step.

Test Running Your Build

Before you begin making the bootable USB with your chosen build, it is always advisable to test run the version you've selected to make sure it's stable and functional. This isn't a critical step but recommended as it will save you a lot of time and effort in case your build isn't compatible with your system in a fundamental way. For this purpose we will be using a Virtual Machine setup.

The first step for this purpose is to download and install the most recent version of the Virtualbox installation file or any other virtual machine