```
-/+ buffers/cache:     412964     483156
Swap:              0          0          0

trim@trimslice:~$ cat /proc/cpuinfo
Processor       : ARMv7 Processor rev 0 (v7l)
processor       : 0
BogoMIPS        : 996.14

processor       : 1
BogoMIPS        : 9.49

Features        : swp half thumb fastmult vfp edsp thumbee vfpv3
vfpv3d16
CPU implementer : 0x41
CPU architecture: 7
CPU variant     : 0x1
CPU part        : 0xc09
CPU revision    : 0

Hardware        : trimslice
Revision        : 0000
Serial          : 0000000000000000
```

We can see that it really has a highly integrated core. The *lspci* command shows only a network controller and core bus information. There is no visible separate unit for sound or video, and even for disk I/O. Just compare it with your x86 PC for a contrast. Its RAM is only 900 MiB, though this box has 1 GB installed. The rest is allocated to video memory. The configuration parameters responsible for the allocation are in the uBoot bootloader's configuration file */boot/boot.scr*:

```
setenv memory mem=384M@0M mem=512M@512M nvmem=128M@384M
setenv video  vmalloc=248M video=tegrafb
setenv console console=ttyS0,115200n8
```

This net-top can be equipped either with an SSD, or a 6.35 cm (2.5") HDD. Let's figure out what exactly CompuLab put inside our system.

```
trim@trimslice:~$ mount
/dev/root on / type ext3 (rw,commit=0)
proc on /proc type proc (rw)
none on /sys type sysfs (rw,noexec,nosuid,nodev)
devtmpfs on /dev type devtmpfs (rw,mode=0755)
none on /proc/sys/fs/binfmt_misc type binfmt_misc
(rw,noexec,nosuid,nodev)
none on /sys/kernel/debug type debugfs (rw)
none on /sys/kernel/security type securityfs (rw)
none on /dev/pts type devpts (rw,noexec,nosuid,gid=5,mode=0620)
none on /dev/shm type tmpfs (rw,nosuid,nodev)
none on /var/run type tmpfs (rw,nosuid,mode=0755)
none on /var/lock type tmpfs (rw,noexec,nosuid,nodev)
fusectl on /sys/fs/fuse/connections type fusectl (rw)
gvfs-fuse-daemon on /home/trim/.gvfs type fuse.gvfs-fuse-daemon
(rw,nosuid,nodev,user=trim)

trim@trimslice:~$ df
Filesystem           1K-blocks      Used Available Use% Mounted on
/dev/root            240407392 227408564    789924 100% /
devtmpfs                447912       500    447412   1% /dev
none                    448060       176    447884   1% /dev/shm
none                    448060       116    447944   1% /var/run
none                    448060         0    448060   0% /var/lock
```

Alright, obviously it has a bigger HDD (250 GB), and it is formatted as an ext3 partition. But the main secret is still unknown—how fast is this net-top? Let's apply the test approach we used in the previous IBM pSeries article (*LFY* January 2012, 'Linux on Power'). We'll run the 7zip archiving utility in benchmark mode. But before the test, let us update the system, making sure we have the correct settings for Ubuntu ARM repositories:

```
trim@trimslice:~$ cat /etc/apt/sources.list
deb http://ports.ubuntu.com/ubuntu-ports/ natty-security universe
main
deb http://ports.ubuntu.com/ubuntu-ports natty-updates universe
main
deb http://ports.ubuntu.com/ubuntu-ports natty main universe
multiverse

## Repository for Trim-Slice users provided by Compulab
deb http://trimslice.com/download/ubuntu/natty binary/
```

Then run *aptitude update && aptitude safe-upgrade*. Perfect. You can install the 7zip archiver: *aptitude install p7zip*. Run it in benchmark mode, as follows:

```
trim@trimslice:~$ time 7zr b

7-Zip (A) 9.04 beta Copyright (c) 1999-2009 Igor Pavlov 2009-05-30
p7zip Version 9.04 (locale=en_IN,Utf16=on,HugeFiles=on,2 CPUs)

RAM size:     875 MB,  # CPU hardware threads:   2
RAM usage:    425 MB,  # Benchmark threads:      2

Dict        Compressing          |        Decompressing
      Speed Usage    R/U Rating  |      Speed Usage    R/U Rating
       KB/s     %   MIPS   MIPS  |       KB/s     %   MIPS   MIPS

22:     633   135    456    615  |      14909   188    716   1346
23:     650   139    475    662  |      14749   189    716   1350
24:     640   141    489    688  |      13711   187    679   1272
25:     593   138    490    677  |      12709   169    708   1195
----------------------------------------------------------------
Avr:          138    477    661               183    705   1291
Tot:          161    591    976
```