

USB cable (if you created the *udev* rule earlier, this will trigger *udev* to detect the phone and create the device node with the right permissions). You can now check if you can list your device via the ADB devices command (remember that ADB can only see your phone when the lock screen is unlocked). If everything has worked well, you should see an output similar to the following (which is for a Geeksphone Keon):

```
$ adb devices
List of devices attached
Full_keon device
```

Building Firefox OS

Depending on your Internet connection, the configuration takes a number of hours to download the files necessary to build Firefox OS (with a slow 150kbps connection, downloading gigabytes of Android repositories can take tens of hours). Waiting is not as much fun as actually doing something, so after you have read through this page and have kicked off the configure script, consider using the time to set up and try out the Firefox OS simulator. Begin familiarising yourself with 'Documentation for app developers' including 'Designing and Building an App'. You could also read up on information related to the upcoming steps.

Cloning the B2G repository

The first step, before you can start your first build, is to clone the B2G repository. This will not fetch everything! Instead, it will fetch the B2G build system and set-up utilities. Most of the actual B2G code is in the main Mozilla *Mercurial* repository.

To clone this repository, use Git and run the following commands in the terminal:

```
git clone git://github.com/mozilla-b2g/B2G.git
cd B2G
```

Once you've retrieved the core B2G build system, you need to configure it for the device on which you plan to install it. To get a list of supported devices, you can use the *config.sh* utility; run the following command from within the B2G directory:

```
./config.sh
```

When you enter the above command, you will get something like the following in the terminal screen:

```
Usage: ./config.sh [-cdflnq] (device name)
Flags are passed through to |./repo sync|

Valid devices to configure are:
- galaxy-s2
```

```
- galaxy-s2
- nexus-4
- nexus-s
- nexus-s-4g
- flo "(Nexus 7 2013)"
- nexus-5
- flame
- otoro
- unagi
- inari
- keon
- peak
- leo
- hamachi
- helix
- wasabi
- fugu
- tara
- pandaboard
- emulator
- emulator -jb
- emulator -kk
- emulator -x86
- emulator -x86-jb
- emulator -x86-kk
```

Now, depending on the device you are working on, you can just build the emulator for it. For example, when you want to build the emulator for a Nexus device, you need to run the following command in the terminal:

```
./config nexus
```

Updating your B2G tree

When the repository is updated to a newer version of B2G, you'll want to update your B2G tree. To do this, you can run the following commands in the terminal:

```
git fetch origin
git checkout origin/master
```

You can check that these worked correctly by running the following command:

```
git show HEAD
```

Starting the build process

Updating your code

If this isn't your very first time building B2G, you might want to pull the latest code before you start to build. To do that, you should update both the B2G tools and the dependencies, using the following two commands: