

Figure 1: Boot menu




Figure 2: Reboot prompt

enter network information like *Host IP*, *Gateway*, *Subnet Mask*, etc. It will also prompt you to enter the hostname; use a name you would like the server to be known by on the network. For this article, I have used 'mylamp' with IP address 210.22.23.24.

Next comes partitioning. I used the *Erase Entire Disk* option; if you have any specific partitioning requirements, feel free to use *Manual partitioning*. After this stage, under *Clock Configuration*, you will be asked about your system time setting. The new user (non-root) creation screen is next; enter your full name, user name (I used 'lampuser') and password. The installer will now show you a software selection screen; select *LAMP Server* and *OpenSSH Server*.

Wait as the progress bars fill up—first for the base system, then for the package installation, and then for the GRUB boot-loader. Once all these are done, it will tell you that it is time

to reboot and take your new server for a ride! Server installation is now complete. Remove the disc and return to your desktop. Let us now remotely configure the server for a LAMP website.

Preparing for deployment

Whether your desktop runs Windows or Linux, you can use the PuTTY SSH client. Download it (from the link at the end), fire it up, and enter the connection details for your server (Figure 3). Click *Open* to connect to the server. This will bring up a terminal prompt that asks you to enter the username. It may throw up an error similar to the one in Figure 5. Just click on Yes. Once the password is accepted, you will be greeted with a shell prompt. The first thing to do is set up a FTP server so we can upload files to the server. Next, let us install phpMyAdmin to manipulate MySQL databases.

FTP service

FTP support is by the *vsftp* daemon (*vsftpd*);

TOP GUN TECHNOLOGIES
 The Best Network & Security Labs in India
Others Promise. We Deliver!

For A Highly Paid Career in India and Abroad
Special 10th Anniversary offer

CCNA	Rs. 8,000/-
CCNA Voice	Rs. 12,000/-
CCNA+CCNP-R&S	Rs. 25,000/-
CCNA+CCNP-Security	Rs. 35,000/-
CCNA+CCNP-SP	Rs. 35,000/-
CCNA+CCNP-Voice	Rs. 40,000/-

All Labs Conducted on CCIE Racks

Congrats to our Latest CCIEs

Mr. Parvej Alam	CCIE # 30714
Mr. Ankit Mukim	CCIE # 30179
Mr. Pongrasath V	CCIE # 28955
Mr. Akhil Verghese	CCIE # 28935
Mr. Ajai Narasimhamurthy	CCIE # 28954
Mr. Rajesh K Joseph	CCIE # 28939
Mr. Suresh Sachan	CCIE # 28686
Mr. Syed Tahir Nassar	CCIE # 28636
Mr. Sumit Kumar	CCIE Security # 28237

We also Offer
Specialized CCIE Training
Special 15 days Bootcamp for
CCIE(R&S) : Rs. 60,000/-

Training Advisor
AJAY PANDEY
 BE, MSE (USA), LLB, CCIE # 14792, (Security / R&S),
 CISSP, CISA, CISM, CCSK, MCSK, ASAP.

Lab Equipped with :
 150 Cisco Routers (2811, 1841, 2621 XM, 3600, 2600, 2500, 1700, 700), 40 Cisco Catalyst Switches (5000, 3750, 3560, 3550, 3000, 2950, 2900), Frame-Relay / ISDN, 12 Firewalls: SonicWall, Watchguard, Cisco PIX 515 E (UR), ASA 5510, PIX 501, 3005 VPN concentrator, 4240, 4210 IPS sensor, Nokia IP 330, Check Point, Cisco WAP / WICs, Cisco Call Manager MCS 7825, Cisco IP Phones 7960, 7961.

Local Accommodation Available
We have Graduated over 85 CCIEs.

BANGALORE
 Visit our Website :
www.topguntechnologies.com
info@topguntechnologies.com
tgtechno@gmail.com
SMS 080- 65616600
☎ 080-23528500

If you find a better Institute to do any of these courses, Join it !