

Important Vyatta configuration commands

To enable and restrict SSH access to Vyatta only from one internal interface (192.168.51.1):

```
Set service ssh listen-address 192.168.51.1
```

To set the time zone:

```
set system time-zone Asia/Calcutta
```

To save the configuration of TFTP server:

```
save tftp://ipaddress/filename
```

To set the Vyatta system domain name:

```
set system domain-name
```

To enable the DHCP server:

```
set service dhcp-server shared-network-name osdhcp
edit service dhcp-server shared-network-name osdhcp
set subnet 192.168.51.0/24
edit subnet 192.168.51.0/24
dns-server 192.168.51.1
default-router 192.168.51.1
set start 192.168.51.201 stop 192.168.51.210
set start 192.168.51.221 stop 192.168.51.230
```

To show the running configuration:

```
show running-config
```

To power off Vyatta:
(Do not forget to commit and save changes before you power off!)

```
poweroff
```

gateway as provided by the ISP:

```
set system gateway-address 121.x.x.1
```

Commit the current configuration using the `commit` command and exit.

Now, check whether the router functions according to your expectations. A simple way to do this could be by using ping. See Figure 2, where the router can ping its internal interface, an external IP address but not google.com. What could be wrong? Any guesses?

There is no DNS! We need to configure DNS server name to resolve this.

Let's see how to configuring the primary and secondary DNS server for Vyatta. Run the following set of commands




Figure 1: Network diagram

```

Partition (auto/union/Parted/Skip) (auto): [ ] 0
vyattavyatta:~$
vyattavyatta:~$
vyattavyatta:~$
vyattavyatta:~$
vyattavyatta:~$
vyattavyatta:~$
vyattavyatta:~$
Welcome to the Vyatta install program. This script
will walk you through the process of installing the
Vyatta image to a local hard drive.

Should you like to continue? (Yes/No) [Yes]: yes
Checking drives: OK
Looking for pre-existing RAID groups... [ 431.000804] end_request: I/O error, disk 0
No RAID found.
The Vyatta image will require a minimum 100MB root.
Would you like us to try to partition a drive automatically
or would you rather partition it manually with parted? If
you have already setup your partitions, you may skip this step.
Partition (auto/union/Parted/Skip) (auto):
  
```

Figure 2: Installation screen

and configure the DNS server IP.

```

configure
Set system name-server 121.x.x.x
Set system name-server 4.2.2.1
commit
save
exit
  
```

The `Save` command saves the existing configuration to the `config.boot` file - to be loaded at the next boot.

Three Network Time Protocol servers are configured automatically as `0.vyatta.pool.ntp.org`, 1 and 2.

Now, connect a system to the Vyatta eth1, assign an IP address and browse the network!

That's all for now folks. We will try and explore more scenarios and configuring of Vyatta in future issues of OSFY. **END** 

Interesting links

Vyatta Download: <http://www.vyatta.org/downloads>
User tips and tricks: <http://vyatta.org/documentation/tips-tricks>

By: Rajesh M Deodhar

The author, who works as an IS auditor and network security trainer—consultant for the last two decades, is a BE in Industrial Electronics, as well as a CISA, CISSP, CCNA and DCL. He can be contacted at rajesh@omegasystems.co.in