

```
$ indexmaker Cisco-MRTG.cfg > index.html
```

Now you can point your Web browser to the right URL, depending on where you put MRTG's *index.html* file, to view MRTG's information. No image file has been created yet, so the output will look unpleasant.

Setting up MRTG for the Cisco ADSL router

As the *cisco-MRTG.cfg* file created by the *cfgmaker* utility contains unwanted information, I had to clean it up. My final MRTG configuration file is given below:

```
# /opt/local/bin/cfgmaker --global "WorkDir: /Users/mtsouk/
Sites/mrtg" OpenSourceFY@cisco

### Global Defaults
EnableIPv6: no
WorkDir: /Users/mtsouk/Sites/mrtg
### Interface 5 >> Descr: 'Dot11Radio0' | Name: 'Do0' | Ip:
'192.168.2.1' | Eth: '00-1d-a2-e7-3f-b0' ###
Target[cisco_5]: 5: OpenSourceFY@cisco:
SetEnv[cisco_5]: MRTG_INT_IP="192.168.2.1" MRTG_INT_
DESCR="Dot11Radio0"
MaxBytes[cisco_5]: 6750000
Title[cisco_5]: Traffic Analysis for WiFi Connection
PageTop[cisco_5]: <h1>Traffic Analysis for WiFi Connection --
cisco877w.mtsouk.local</h1>
<div id="sysdetails">
  <table>
    <tr><td>System:</td> <td>cisco877w.mtsouk.
local</td></tr>
    <tr><td>Maintainer:</td><td></td></tr>
    <tr><td>Description:</td> <td>Dot11Radio0 </
td></tr>
    <tr><td>ifType:</td> <td>Radio Spread Spectrum
(802.11) (71)</td></tr>
    <tr><td>ifName:</td> <td>Do0</td></tr>
    <tr><td>Max Speed:</td><td>6750.0 kBytes/s</
td></tr>
    <tr><td>Ip:</td><td>192.168.2.1 {}</td></tr>
  </table>
</div>

### Interface 15 >> Descr: 'Dialer1' | Name: 'Dialer 1' | Ip:
'' | Eth: '' ###

Target[Cisco-linespeed]: 1.3.6.1.2.1.2.2.1.10.14&1.3.6.1.2.1.2.
2.1.16.14: OpenSourceFY@cisco:
SetEnv[Cisco-linespeed]: MRTG_INT_IP="" MRTG_INT_
DESCR="Dialer1"
MaxBytes[Cisco-linespeed]: 3145728
Title[Cisco-linespeed]: Traffic Analysis for ADSL Internet
connection -- Cisco 877W
Legend1[Cisco-linespeed]: Average
```

```
Legend2[Cisco-linespeed]:
Legend3[Cisco-linespeed]: Maximum
Legend4[Cisco-linespeed]:
Legend1[Cisco-linespeed]: TX:
Legend0[Cisco-linespeed]: RX:
PageTop[Cisco-linespeed]: <h1>Traffic Analysis for ADSL
Internet connection</h1>
<div id="sysdetails">
  <table>
    <tr><td>System:</td><td>Cisco 877W</td></tr>
    <tr><td>Maintainer:</td><td>Mihalis
Tsoukalos</td></tr>
    <tr><td>Description:</td> <td>Cisco-
linespeed</td></tr>
    <tr><td>ifType:</td> <td>ADSL connection</
td></tr>
    <tr><td>ifName:</td> <td>Dialer1</td></tr>
    <tr><td>Max Speed:</td><td>250.00 kBytes/s</
td></tr>
  </table>
</div>
```

The aforementioned configuration file monitors my ADSL as well as my Wi-Fi traffic. The Wi-Fi connection was automatically found by the *cfgmaker* utility but setting up the ADSL was more complicated. The Cisco SNMP OIDs (Object Identifiers) that interest me are the following:

- 1.3.6.1.2.1.2.2.1.10.14: returns the incoming traffic for the ADSL connection.
- 1.3.6.1.2.1.2.2.1.16.14: returns the outgoing traffic for my ADSL connection.

Finding those two number sequences is a little difficult, so I will explain how I found them:

- I Googled 'IF MIB download' and found the following URL: <http://www.oidview.com/mibs/0/IF-MIB.html>
- I knew that I was looking for *In* and *Out Octets* and by looking on the Web page, I found that I was interested in sequences 1.3.6.1.2.1.2.2.1.10 (ifInOctets) and 1.3.6.1.2.1.2.2.1.16 (ifOutOctets), respectively.
- The last thing to do was adding the desired Cisco interface number at the end of each sequence. The available interfaces can be found by executing the following Cisco IOS command:

```
cisco877w#show snmp mib ifmib ifindex
ATM0: Ifindex = 6
ATM0-adsl: Ifindex = 12
ATM0-atm layer: Ifindex = 8
ATM0-0-atm subif: Ifindex = 9
FastEthernet0: Ifindex = 1
Null0: Ifindex = 7
Dialer1: Ifindex = 14
FastEthernet1: Ifindex = 2
```