

driver: vmxnet

version: 2.0.1.1

firmware-version: N/A

bus-info: 0000:00:11.0

/dev/ttyS1, UART: unknown, Port: 0x02f8, IRQ: 3

/dev/ttyS2, UART: unknown, Port: 0x03e8, IRQ: 4

/dev/ttyS3, UART: unknown, Port: 0x02e8, IRQ: 3

ttys0 - first serial port

port :0x03f8 - i/o address

IRQ-4 - interrupt number of serial port

—Parvez Ansari, iamnetizen@gmail.com



Defrag your databases

Whenever you change the structure of a MySQL database, or remove a lot of data from it, the files can become fragmented resulting in a loss of performance, particularly when running queries. Just remember to run the optimiser every time you make any changes to the database:

```
mysqlcheck -o <dbname>
```

—Remin Raphael, remin13@gmail.com



Restoring defaults in KDE4

Sometimes while personalising your panel you may accidentally delete it. And then you may want to restore the distro's default panel back again. This is how we do it on KDE 4.

Log out and open a command prompt using Ctrl+Alt+F1. Then log in as the same user and run this command:

```
rm /kde4/share/config/plasma-appletsrc
```

This is the file where configurations are stored for any user. If you remove it, the default settings will reappear. Use Ctrl+Alt+F7 in order to access the X server to log back in.

—Roshan Kumar Singh,
singh.roshan08@gmail.com



I/O address, IRQ number of serial ports

Those of you who are writing device drivers for serial ports should know the I/O address of each serial port and its IRQ number. To find out, type the following command:

```
setserial -g /dev/ttyS*
```

You should get something similar to what's shown below:

```
/dev/ttyS0, UART: 16550A, Port: 0x03f8, IRQ: 4
```

—Veeraiyan C, veeraiyan@gmail.com



What have you done?

The *history* command will give you the complete history of all the commands you've run till now along with their serial numbers. For example:

```
$ history
1 su -
2 kmail
3 rm -rf /kde4/share/apps/kmail/mail
4 rm -rf /mozilla/
5 rpm -qa | grep flash
6 top
7 rpm -qa | grep rpm
8 ps -A | grep rpm
9 cd /var/lib/flash-player-plugin/
10 su -
```

There is a history manipulation command too called *fc*. Type:

```
fc 9
```

This will allow you to edit the command using the Vim editor. When you save and exit, it runs the command automatically.

—Ashraf Ali, ashrafd2005@gmail.com



Share Your Linux Recipes!

The joy of using Linux is in finding ways to get around problems—take them head on, defeat them! We invite you to share your tips and tricks with us for publication in LFY so that they can reach a wider audience. Your tips could be related to administration, programming, troubleshooting or general tweaking. Submit them at www.linuxforu.com. The sender of each published tip will get an LFY T-shirt.