

report of all devices and the CPU, since the last boot.

As you can see in Figure 4 the report also presents me the blocks-read per second (Blk_read/s), the blocks-written per second (Blk_wrtn/s), the total blocks-read (Blk_read) and total blocks-written (Blk_wrtn) since the last boot. This per-second report can be very handy in taking a decision for an upgrade.

I personally find this command very useful in figuring out which partition of my hard disk is under heavy I/O load. So I can use this report for either upgrading my disk or putting that mount on a separate disk. Figure 5 shows the output when I ran this command on my FTP server. (Just look at the output very carefully—it's self-explanatory.)

You can see /dev/sda2 is the partition with maximum blocks-read per second (Blk_read/s) and maximum blocks-read (Blk_read). Why?

I now issue the following command to tell you the reason:

```
# e2label /dev/sda2
/var
```

You can see that we have /var mounted on this partition since it's an FTP server. So these large numbers are justified. I can use these in the future to mount my /var on a separate high speed HDD if this number goes even higher.

x86info

x86info is a very useful tool that can be used to display a range of information about the CPUs present in an x86 system. The following is the output on my system:

```
x86info v1.20. Dave Jones 2001-2006
Feedback to <davej@redhat.com>.
```

```
Found 2 CPU(s)
```

```
-----
CPU #1
Family: 15 Model: 11 Stepping: 2
CPU Model : Athlon 64 CH7-CG
Processor name string: AMD Athlon(tm) 64 X2 Dual Core Processor 5000+
```

Feature flags:

```
fpu vme de pse tsc mtr pae mce cx8 apic sep mtr pge mca cmov pat
pse36 clflush mmx fxsr sse sse2 ht sse3 cmovchgt16b
Extended feature flags:
syscall nx mmxext Fast Fsave/Fxstor rdtscl im3dnowext 3dnow lahf/sahf
CMP legacy svm ExtApicSpace LockMovCr0 3DNowPrefetch
The physical package has 2 cores
```

```
-----
CPU #2
Family: 15 Model: 11 Stepping: 2
CPU Model : Athlon 64 CH7-CG
Processor name string: AMD Athlon(tm) 64 X2 Dual Core Processor 5000+
Feature flags:
```

```
fpu vme de pse tsc mtr pae mce cx8 apic sep mtr pge mca cmov pat
pse36 clflush mmx fxsr sse sse2 ht sse3 cmovchgt16b
Extended feature flags:
syscall nx mmxext Fast Fsave/Fxstor rdtscl im3dnowext 3dnow lahf/sahf
CMP legacy svm ExtApicSpace LockMovCr0 3DNowPrefetch
The physical package has 2 cores
```

```
WARNING: Detected SMP, but unable to access cpuid driver.
Used Uniprocessor CPU routines. Results inaccurate.
```

This command is very useful in finding the L1/L2 cache of the CPU, which comes in very handy while configuring TLBs, etc. Just try running **x86info -c** to find the cache information of the CPU:

```
x86info v1.20. Dave Jones 2001-2006
Feedback to <davej@redhat.com>.
```

```
Found 2 CPU(s)
```

```
-----
CPU #1
Family: 15 Model: 11 Stepping: 2
CPU Model : Athlon 64 CH7-CG
Processor name string: AMD Athlon(tm) 64 X2 Dual Core Processor 5000+
```

Feature flags:

```
fpu vme de pse tsc mtr pae mce cx8 apic sep mtr pge mca cmov pat
pse36 clflush mmx fxsr sse sse2 ht sse3 cmovchgt16b
Extended feature flags:
syscall nx mmxext Fast Fsave/Fxstor rdtscl im3dnowext 3dnow lahf/sahf
CMP legacy svm ExtApicSpace LockMovCr0 3DNowPrefetch
Instruction TLB: Fully associative, 32 entries.
Data TLB: Fully associative, 32 entries.
```

L1 Data cache:

```
Size: 64Kb 2-way associative
lines per tag=1 line size=64 bytes.
```

L1 Instruction cache:

```
Size: 64Kb 2-way associative
lines per tag=1 line size=64 bytes.
```

L2 (on CPU) cache:

```
Size: 512Kb 8-way associative.
lines per tag=1 line size=64 bytes.
```

The physical package has 2 cores.

```
-----
CPU #2
Family: 15 Model: 11 Stepping: 2
CPU Model : Athlon 64 CH7-CG
Processor name string: AMD Athlon(tm) 64 X2 Dual Core Processor 5000+
```

Feature flags:

```
fpu vme de pse tsc mtr pae mce cx8 apic sep mtr pge mca cmov pat
pse36 clflush mmx fxsr sse sse2 ht sse3 cmovchgt16b
Extended feature flags:
syscall nx mmxext Fast Fsave/Fxstor rdtscl im3dnowext 3dnow lahf/sahf
CMP legacy svm ExtApicSpace LockMovCr0 3DNowPrefetch
```