

```
anjali@anjali-Lenovo-IdeaPad-S510p:~$ ftp 192.168.50.2
```

Figure 4: The program allows a user to transfer files to and from a remote network site

```
anjali@anjali-Lenovo-IdeaPad-S510p:~$ free
              total        used        free      shared  buffers   cached
Mem: 3945920  2118400    1827520    224000      48348    118976
-/+ buffers/cache: 951484    2994436
Swap: 15387452      0    15387452
```

Figure 5: The *free* command shows the free, total and swap memory information in bytes

5. The *free* command

Free displays the total amount of free and used physical and swap memory in the system, as well as the buffers used by the kernel. The shared memory column represents either the MemShared value or the Shmem value taken from the */proc/meminfo* file. The value is zero if none of the entries is exported by the kernel.

6. The *top* command

The *top* program provides a dynamic real-time view of a running system. It can display system summary information as well as a list of processes or threads currently being managed by the Linux kernel. The kind of information shown, as well as the types, order and volume of information displayed for processes, is all user-configurable; and that configuration can be made persistent across restarts.

7. The *lsdf* command

Lsf revision 4.86 lists, on its standard output file, information about files opened by processes for the following UNIX dialects:

- Apple Darwin 9 and Mac OS X 10 [567]
- FreeBSD 4.9 and 6.4 for x86-based systems
- FreeBSD 8.2, 9.0 and 10.0 for AMD64-based systems
- Linux 2.1.72 and above for x86-based systems
- Solaris 9, 10 and 11

An open file may be a regular file, a directory, a block special file, a character special file, an executing text reference, a library, a stream or a network file (Internet socket, NFS file or UNIX domain socket). Instead of a formatted display, *lsdf* will produce output that can be parsed by other programs. In addition to producing a single output list, *lsdf* will run in repeat mode, during which it will produce output, delay, then repeat the output operation until stopped with an interrupt or quit signal.

8. The *pwd* command

This prints the full file name of the current working directory.

9. The *rm* command

The *rm* command removes each specified file. By default, it does not remove directories. If the *-i* or *--interactive=once* option is given, and there are more than three files, then *rm*

```
top - 11:07:28 up 21 min, 2 users, load average 0.17, 0.19, 0.27
Tasks: 286 total, 1 running, 285 sleeping, 0 stopped, 0 zombie
MiB Mem: 0.7 us, 0.4 sy, 0.0 ni, 90.3 kd, 0.3 wa, 0.0 hi, 0.0 si, 0.0 st
MiB Mem: 3945920 total, 2227768 used, 1718152 free, 2824 buffers
MiB Swap: 15387452 total, 0 used, 15387452 free, 15348844 cached Mem

PID USER      PR  NI    VIRT    RES    SHR     S    %CPU  %MEM     time+  COMMAND
1196 root      20   0 370912 51000  40948   S    1.7   1.3   0:14.99  top
3180 anjali    20   0 664556 32500  24056   S    1.0   0.8   0:00:42  chrome-term
7581 anjali    20   0 1871896 174716 919408   S    0.7   4.4   0:22:05  chrome
2430 anjali    20   0 258040 88632  47580   S    0.3   2.2   0:16:06  cmprls
2865 anjali    20   0 626166 94666  382028   S    0.3   2.4   0:03:38  chrome
top - 11:03:48 up 22 min, 2 users, load average 0.22, 0.20, 0.24
Tasks: 128 total, 1 running, 127 sleeping, 0 stopped, 0 zombie
MiB Mem: 0.3 us, 0.5 sy, 0.0 ni, 99.2 kd, 0.0 wa, 0.0 hi, 0.0 si, 0.0 st
MiB Mem: 3945920 total, 2252560 used, 1693360 free, 50400 buffers
MiB Swap: 15387452 total, 0 used, 15387452 free, 15348844 cached Mem

PID USER      PR  NI    VIRT    RES    SHR     S    %CPU  %MEM     time+  COMMAND
2581 anjali    20   0 1871896 174888 92084   S    0.3   4.4   0:23:55  chrome
2600 anjali    20   0 477216 90388  79364   S    0.1   2.5   0:00:11  chrome
3180 anjali    20   0 664446 32660  24056   S    0.0   0.8   0:01:10  chrome-terminal
2045 anjali    20   0 323372 10348  8096   S    0.0   0.3   0:00:14  gnome-keyring-d
```

Figure 6: The *top* command displays the processor activity of your system as well as the tasks managed by the kernel, in real-time

```
lsdf -m 288 anjali  mem  RSL  x.9  203121  anshelb  /jagadshah/anaconda/python3.6-3.3.3.x.8
lsdf -m 288 anjali  mem  RSL  x.9  10000  anshelb  /jagadshah/anaconda/python3.6-3.3.3.x.8
lsdf -m 288 anjali  mem  RSL  x.9  88888  anshelb  /jagadshah/anaconda/python3.6-3.3.3.x.8
lsdf -m 288 anjali  mem  RSL  x.9  10000  anshelb  /jagadshah/anaconda/python3.6-3.3.3.x.8
lsdf -m 288 anjali  mem  RSL  x.9  10000  anshelb  /jagadshah/anaconda/python3.6-3.3.3.x.8
lsdf -m 288 anjali  mem  RSL  x.9  10000  anshelb  /jagadshah/anaconda/python3.6-3.3.3.x.8
```

Figure 7: The *lsdf* command displays a list of all open files

```
anjali@anjali-Lenovo-IdeaPad-S510p:~$ pwd
/home/anjali
anjali@anjali-Lenovo-IdeaPad-S510p:~$
```

Figure 8: The *pwd* command returns the current working directory

```
anjali@anjali-Lenovo-IdeaPad-S510p:~$ rm -i hello.txt
rm: remove regular file 'hello.txt'?
```

Figure 9: Using the *-i* option to get confirmation before removing it

```
anjali@anjali-Lenovo-IdeaPad-S510p:~$ service apache2 start
* Starting web server apache2
*
anjali@anjali-Lenovo-IdeaPad-S510p:~$ service apache2 restart
* restarting web server apache2
anjali@anjali-Lenovo-IdeaPad-S510p:~$ service apache2 stop
* Stopping web server apache2
*
anjali@anjali-Lenovo-IdeaPad-S510p:~$
```

Figure 10: Starting, restarting, stopping Apache2 server on Ubuntu

asks the user whether to proceed with the entire operation. If the response is not in the affirmative, the entire command is aborted. Using options *-r* and *-f* will remove the file forcefully without confirmation.

10. The *service* command

The *service* command controls the starting, stopping or restarting of a 'service'. This command makes it possible to start, restart or stop a service without restarting the system, for the changes to take effect. 

References

- [1] <http://www.tecmint.com/>

By: Anjali Menon

The author is an open source enthusiast and a Linux kernel contributor. You can contact her at cse.anjalimenon@gmail.com.