



Figure 1: Sangoma card

Download Asterisk by running the command given below:

```
wget http://downloads.asterisk.org/pub/telephony/asterisk/
old-releases/asterisk-1.8.21.0.tar.gz
```

Install *libpri* by following the steps given below:

```
tar xzvf libpri-1.4.12.tar.gz
cd libpri-1.4.12
make clean
make
make install
```

Install the complete Dahdi by running the following commands:

```
tar xzvf dahdi-linux- complete-2.6.0+2.6.0.tar.gz
cd dahd-linux- complete-2.6.0+2.6.0
make clean
make
make install
make config
```

Install Asterisk by running the following commands:

```
tar xzvf asterisk-1.8.21.0.tar.gz
cd asterisk-1.8.21.0
make clean
./configure
make
make install
make samples(for only fresh installation)
```

Downloading Wanpipe

Go to `cd /usr/src` and download Wanpipe by running:

```
wget ftp://ftp.sangoma.com/linux/current_wanpipe/wanpipe-
7.0.3.tgz
```

Install the dependencies by running the following commands:

```
yum -y install kernel-devel- $(uname -r) libtool* gcc
```

```
make patch perl bison gcc-c++ ncurses-devel flex libtermcap-devel
autoconf*
automake*"
```

Place the card properly and power on the system. Check whether the system detects the card, as follows:

```
lspci | grep Sangoma.
```

Next, check whether Dahdi detects the card *Dahdi_tool*. Go to the directory `cd /usr/src` and install Wanpipe by giving the following commands:

```
tar xzvf wanpipe-7.0.3.tgz
cd /wanpipe-7.0.3/
make clean.
```

Now run the following command:

```
./Setup install "
```

If it prompts 'Yes' press 'y' and proceed to the next level.



Note: The next step is to configure the port for PRI calls. Please note that in the E1 card, 30 channels are used for the PRI line.

Steps you need to follow to configure the port of the card

1. You will see the Wanpipe driver installation splash screen. Press 'y' to continue.
2. You will be presented with a dependency check with pass/fail results. If there are any failures, you must exit and install the missing dependencies manually. Press *Enter* to continue. Press *Enter* at the following screen for the default kernel source location. If there are any error messages that result, it means some Linux kernel development packages are missing. It also means that the 'Preparing your operating system for software packages' step above has failed to download your kernel-development packages. If this happens, you must search online for the kernel-development packages for your kernel, and then download and install them using (*rpm -i...*). Press *Enter* to continue.
3. Next, you will be presented with seven different options on how to install the Wanpipe driver. Select Option 2 to install the Wanpipe driver for Asterisk.
4. You will be asked to provide the location of your Dahdi software package. If you have downloaded and installed Dahdi in */usr/src/*, simply press the number pertaining to the location. In this example, the user has Dahdi version 2.7.0 installed on the system. If your Dahdi installation resides in another directory, press 'm', and then manually enter the full path. If you have multiple