

5. Test by leaving the geofence and returning once.

Upgrade: Add “if it’s after 11 PM, use dim light only” so nobody gets flashbanged.

7) Door open → Light on

- Goal: Opening the main door triggers a short, useful light action.
- Ingredients: door sensor (or smart lock), entry light.
- Trigger: door opens / accessory changes.
- Actions: entry light on; optional chime/notification.

Apple explicitly suggests you can use “When an accessory changes” to run a scene – for example, run a scene when you unlock the front door.

Steps

1. Install door sensor on frame + door with tight alignment.
2. Trigger: door opens.
3. Condition: after sunset OR only when someone is home (so it’s not a beacon when away).
4. Action: turn on entry light for 2–5 minutes.
5. Add “cooldown”: don’t retrigger repeatedly within 60 seconds (prevents spam when people hover at the door).

Upgrade: Add “if Away Mode is ON, send notification” (and do not turn on lights unless you want that deterrent).

8) Bedroom “nap mode”

- Goal: A single command makes the bedroom nap-ready.
- Ingredients: bedroom lights, optional AC, optional speaker.
- Trigger: voice phrase (“Nap time”).
- Actions: dim lights, set temp, silence notifications/announcements (if supported).

Steps

1. Create a Nap Scene: bedroom light 10–20%, everything else unchanged.
2. Routine activates the scene + sets AC to a gentle preset for 45–90 minutes.
3. Add an automatic exit: restore lights/AC at end of nap window.
4. Condition: only between 12 PM–6 PM (so nobody triggers nap mode at 2 AM).
5. Keep it simple; the charm is one-tap comfort.

Upgrade: Add a bedside button as the trigger so you don’t need voice at all.

9) Smart plug safety timer

- Goal: If a high-risk plug is left on (iron, heater), it shuts off after X minutes.
- Ingredients: smart plug (rated appropriately), the appliance.
- Trigger: plug turns on.
- Condition: only during certain hours (optional).
- Action: turn off after 20–40 minutes; send alert.



Steps

1. Choose the right device: do not put heavy loads on cheap plugs. If you’re unsure about load ratings, skip this and use a dedicated timer switch installed by an electrician.
2. Trigger: plug ON.
3. Action: wait 30 minutes → plug OFF.
4. Optional action: send notification “Auto-off triggered.”
5. Test with a safe low-power device first.

Upgrade: Add a “manual override” routine: “Keep on for 2 hours” (for a controlled exception).

10) Guest / Cleaner mode

- Goal: Let the home behave differently when staff/guests are present – without giving them full control.
- Ingredients: a virtual switch/toggle (in HA) or a scene/routine toggle, optional camera rules, lights, motion rules.
- Trigger: manual toggle (tap in app) or a schedule (maids often have fixed times).
- Actions: disable indoor cameras, keep motion lights active, prevent Away Mode from arming.

Steps

1. Create a toggle called Guest Mode / Cleaner Mode (scene or helper).
2. When Guest Mode is ON:
 - indoor cameras OFF
 - motion lights still work
 - Away Mode automation is blocked via a condition (“only if Guest Mode is OFF”)
3. When Guest Mode turns OFF: restore normal security rules.
4. Add a scheduled reminder: “Cleaner Mode still on?” at 2 PM, so you don’t forget.
5. Test the logic by simulating “everyone leaves” while Guest Mode is ON.

This is where conditions shine: in Home Assistant, conditions are explicitly designed to prevent execution when states don’t match, and triggers fire first then conditions gate the run. 