

```

MOV C, ACC.2
MOV DB6,C
MOV C, ACC.3
MOV DB7,C
CLR EN
NOP
SETB EN ; PULSE THE ENABLE LINE
LCALL MDELAY
POP ACC
RET
;*****LCD SUBROUTINES*****
DAT: PUSH ACC ; SAVE ACCUMULATOR
SETB EN
SETB RS ; SELECT SEND DATA
MOV A, BUF ; PUT DATA BYTE IN ACC
MOV C, ACC.4 ; LOAD HIGH NIBBLE ON
DATA BUS
MOV DB4,C ; ONE BIT AT A TIME
USING...
MOV C, ACC.5 ; BIT MOVE OPERATIONS
MOV DB5,C
MOV C, ACC.6
MOV DB6,C
MOV C, ACC.7
MOV DB7,C
CLR EN
NOP
SETB EN ; PULSE THE ENABLE LINE
MOV C, ACC.0 ; SIMILARLY, LOAD LOW
NIBBLE
MOV DB4,C
MOV C, ACC.1
MOV DB5,C
MOV C, ACC.2
MOV DB6,C
MOV C, ACC.3
MOV DB7,C

```

```

CLR EN
NOP
SETB EN ; PULSE THE ENABLE LINENOP
LCALL MDELAY
POP ACC
RET
;*****LCD SUBROUTINES*****
CLEAR: MOV BUF,#01H
LCALL CMD
RET
;*****LCD SUBROUTINES*****
DDELAY: MOV R5,#41D ; 4.1 MS DELAY
QT2: MOV R6,#50D
QT1: DJNZ R6,QT1
DJNZ R5,QT2
RET
;*****LCD SUBROUTINES*****
MDELAY: MOV R5,#26D
QT22: MOV R6,#50D
QT11: DJNZ R6,QT11
DJNZ R5,QT22
RET
;*****LCD SUBROUTINES*****
INIT: MOV BUF,#30H ; FUNCTION
SET - DATA BITS, LINES, FONTS
LCALL CMD
ACALL DDELAY ; INITIAL DELAY 4.1MSEC
MOV BUF,#30H ; FUNCTION SET -
DATA BITS, LINES, FONTS
LCALL CMD
ACALL DDELAY ; INITIAL DELAY 4.1MSEC
MOV BUF,#30H ; FUNCTION SET -
BITS, LINES, FONTS
LCALL CMD
ACALL DDELAY ; INITIAL DELAY 4.1MSEC
MOV BUF,#28H ; 2 LINES 5X7, 4-BIT
MODE

```

```

LCALL CMD
MOV BUF,#0CH ; DISPLAY ON
LCALL CMD
MOV BUF,#01H ; CLEAR DISPLAY, HOME
CURSOR
LCALL CMD
MOV BUF,#06H ; SET ENTRY MODE
LCALL CMD ; INCREMENT CURSOR RIGHT,
NO SHIFT
RET
ORG 0320H
MSG1: DB 'SOLAR CHARGE ',00H
MSG2: DB 'CONTROLLER-EFV ',00H
MSG3: DB 'LOAD ON ',00H
MSG4: DB 'CHARGING ',00H
MSG5: DB 'BATTERY FULL ',00H
MSG6: DB 'BAT.LOW-LOAD OFF',00H
MSG7: DB 'Volts: ',00H
ORG 0400H
RCHAR: DB 04D,31D,17D,31D,17D,31D,
17D,31D ; CHARGING
DB 04D,31D,31D,31D,31D,31D,
31D,31D ; FULL
DB 31D,31D,14D,04D,04D,14D,
31D,31D ; LOAD
DB 04D,31D,17D,17D,17D,17D,
17D,31D ; LOW BATT
DB 31D,31D,31D,31D,31D,31D,
31D,31D
DB 31D,31D,31D,31D,31D,31D,
31D,31D
DB 31D,31D,31D,31D,31D,31D,
31D,31D
DB 031D,31D,31D,31D,31D,31D,
31D,31D,00H
END

```

Want to have an edge over others?

Master LINUX



Read LINUX For You

For more info, log on to:

www.linuxforu.com

ASIA'S FIRST
LINUX MAGAZINE



LINUX
THE COMPLETE MAGAZINE ON LINUX FOR YOU
ForYou