

Reveal the Time Secret of Frequency Footprint




GSP-930 3GHz Spectrum Analyzer

GSP-930 is a 3GHz Spectrum Analyzer designed upon a new generation platform. The high stability, large screen display, light weight and compact size of GSP-930 benchmark a new standard for 3GHz spectrum analyzer in the market. Its advanced features, Spectrogram and Topography, greatly expand the application range and elevate the importance of a spectrum analyzer in the role as the irreplaceable RF analysis instrument.

GSP-930 provides a high frequency-stability of 25ppb (0.025ppm) and a very low noise floor of -142dBm (Pre-amplifier on) as the high sensibility measurement base. The flexible selection among 58 RBW ranges along with Spectrogram and Topographic features enable GSP-930 to capture and display transient, drifting and hopping signals in detail. The mixture of frequency domain information and time domain information facilitates the tracing of RF signal variations over time. Other useful features like Spectrum Emission Mask (SEM), Power Measurements, AM/FM Analysis and TOI/CNR/CSO/CTO measurements, make GSP-930 a useful instrument right fit into a broad range of applications.


FEATURES

- Frequency Range: 9kHz ~ 3GHz
- High Frequency Stability: 25ppb (0.025ppm)
- RBW: 10Hz~10kHz in 1-3 Steps, 10kHz~1MHz in 10% Adjustable Steps
- Phase Noise: -88dBc/Hz @1GHz, 10kHz Offset
- Built-in Measurement Functions: Channel Power, N-dB Bandwidth, OCBW, ACPR, SEM, TOI, CNR, CTB, CSO
- Built-in Spectrogram and Topographic Display Modes
- 1Hz Resolution Marker Counter
- AM/FM Demodulation and Analysis
- 886MHz IF Output for User's Extended Applications
- Various Interface: USB Host/Device, RS-232C, LXI, Micro SD, GPIB(Optional)
- Optional 6GHz RF Power Sensor, Tracking Generator, Battery Pack



Topographic Mode

Display shows the spectral color varies with signal occurrence times, which shows how the signal behaves from the aspect of frequency.



Spectrogram Mode

Display shows spectral density of a signal varies with time. The instant frequency-change is traced in the display.

For more details, please contact your nearest distributor or you may directly write to India_marketing@goodwill.com.tw

Bangalore : Integrated Services & Consultancy, 080- 23420746, sales@isc4esaindia.com

Chennai : Vamara Techware, +91 9894388839, sales@vamara.in

Hyderabad : GSAS Micro Systems, +91-9704414410, satya@gsasindia.com

Kolkata : Arihant Trading Company, +91-9830033381, gautam1966@gmail.com

New Delhi : Avante Global Services Pvt Ltd, 011-26473068, pkg@avante.in

Thiruvananthapuram : innovative instruments inc, 0471-2316385, instrument_inc@vsnl.net

GW INSTEK

Simply Reliable

GOOD WILL INSTRUMENT CO., LTD.

www.gwinstek.com