



Single Phase Multifunction Meter



EM08



EM08D

Features

- 10 Parameters in One Meter
- Measures V, A, PF, Hz, KW, KVA, KVAh, KWh, KVAh & KVAh
- Auto Scroll / Manual Scroll Display (User Selectable)
- Reduces Panel Space and Wiring Time
- State of The Art Microcontroller Design
- User Programmable CT Ratio (1.00 - 99.99)
- Ideal for Testing of Electrical Appliances
- TRMS Reading
- LCD Display with Backlight (20mm Digit Height)
- RS 485 Port (5kV Isolated) (Optional), please inquire sales@mecoinst.com
- MODBUS RTU Protocol (Optional), please inquire sales@mecoinst.com

Applications

- Appliance Testing
- Energy Audit
- QC
- Studying Energy Efficiency of Electrical Equipment
- Building Management Systems
- Power Management
- Generator / Motor Characteristics
- Plant Maintenance
- Education / Teaching

Specifications

Functions	Input Range			Accuracy
RMS Voltage	50.0 ~ 300 Vrms			± 0.2% of F.S. + 1 dgt.
RMS Current (any one range only)	1A (0.05 ~ 1.2 Arms)	5A (0.25 ~ 6.0 Arms)	10A (0.50 ~ 12 Arms)	± 0.2% of F.S. + 1 dgt.
Active Power	0.005 ~ 0.300 KW	0.015 ~ 1.5 KW	0.050 ~ 3.000 KW	± 0.5% of F.S. + 1 dgt. (Cosφ=0.3 to 1.000)
Apparent Power	0.005 ~ 0.300 KVA	0.015 ~ 1.5 KVA	0.050 ~ 3.000 KVA	± 0.5% of F.S. + 1 dgt.
Reactive Power	0.005 ~ 0.300 KVar	0.015 ~ 1.5 KVar	0.050 ~ 3.000 KVar	± 1.0% of F.S. + 1 dgt. (Sinφ=0.3 to 1.000)
Power Factor	0.3 Lag ~ 1.0 ~ 0.3 Lead			± 0.01 PF + 1 dgt.
Line Frequency	45.00 ~ 65.00 Hz			± 0.1 Hz
Active Energy (KWh)	0000 ~ 9999 KWh			Class 1
Apparent Energy (KVAh)	0000 ~ 9999 KVAh			
Reactive Energy (KVArh)	0000 ~ 9999 KVArh			

MECO INSTRUMENTS PRIVATE LTD.

Plot No. EL-1, MIDC Electronic Zone, TTC Indl. Area, Mahape, Navi Mumbai 400 710. (INDIA)
Tel : 0091-22-27673311-16 (Sales), 27673300 (Board) ● Fax : 0091-22-27673310, 27673303
Email : sales@mecoinst.com ● Web : www.mecoinst.com