

rated voltage ranges are given, these should be separated by a solidus (/). For example, multiple rated voltage of 120/230/240V means that the equipment is designed to connect to an AC mains supply having a voltage of 120V or 230V or 240V, usually after internal adjustment.

If the appliance can be adjusted for different rated voltages, the voltage to which the appliance is adjusted should be clearly discernible.

If the appliance needs to be connected to more than two supply conductors, or if it requires multiple supplies, it should have a connection diagram affixed to it, unless the correct mode of connection is obvious.

2. Symbol for nature of supply, for DC only. It should be placed next to the marking for rated voltage
3. Rated frequency or rated frequency range in hertz, unless the equipment is designed for DC only
4. Maximum rated power in watts or rated current in amperes

Wiring terminal markings

Protective earthing and bonding terminals. A wiring terminal intended for connection of a protective earthing conductor should be indicated by symbol . It is not a requirement to mark terminals for the protective bonding conductor but when such terminals are marked, symbol  should be used. These symbols should not be located on screws or other parts that might be removed when conductors are connected.

Terminals for AC mains supply conductors. For permanently connected equipment and equipment with ordinary non-detachable power supply cord:

1. Terminals intended exclusively for connection of AC mains supply neutral conductor, if any, should be indicated by capital letter N; and
2. On three-phase equipment if incorrect phase rotation would cause overheating or other hazard, terminals intended for connection of AC mains supply line conductors should be marked such that, in conjunction with any installation, the sequence of

Table II Symbols		
Symbol	Reference	Description
	IEC 60417-5031	Direct current
	IEC 60417-5032	Alternating current
	IEC 60417-5033	Both direct and alternating current
		Three-phase alternating current
	IEC 60417-5017	Earth (ground) terminal
	IEC 60417-5019	Protective conductor terminal
	IEC 60417-5020	Frame or chassis terminal
	IEC 60417-5021	Equipotentiality
	IEC 60417-5007	On (supply)
	IEC 60417-5008	Off (supply)
	IEC 60417-5172	Equipment protected throughout by double insulation or reinforced insulation
		Caution, risk of electric shock
	IEC 60417-5041	Caution, hot surface
	ISO 7000-0434	Caution, risk of danger (see note)
	IEC 60417-5268	In position of a bi-stable push control
	IEC 60417-5269	Out position of a bi-stable push control

phase rotation is unambiguous.

These indications should not be located on screws or other parts that might be removed when conductors are connected.

Terminals for DC mains supply conductors. For permanently connected equipment and equipment with ordinary non-detachable power supply cord:

1. Terminals intended exclusively for connection of DC mains supply should be marked to indicate polarity.
2. If a single terminal is provided both as a mains protective earthing terminal in the equipment and for connection to one pole of the DC mains supply, it should be marked as  in addition to polarity marking.

Again, these indications should not be located on screws or other parts that might be removed when conductors are connected.

Field wiring terminal boxes. If the temperature of the terminal or the enclosure of a field wiring terminal

box or compartment exceeds 60°C in normal condition at an ambient temperature of 40°C or the maximum rated temperature, if higher, there should be marking for minimum temperature rating of the cable to be connected to the terminals. The marking should be visible before and during connection or beside the terminals.

Hazardous terminals. Terminals which are hazardous—live under normal operating conditions, except terminals for mains supply—should be marked with .

Output terminals. Output terminals provided for supply to other apparatus, except mains supply, should be marked with nominal output voltage and maximum output current, unless the terminals are marked with the type reference of the apparatus that are permitted to be connected.

Socket outlets providing mains power to other apparatus should be marked with the power and current that can be drawn. If only one terminal is provided for supply to other apparatus, the marking can be put on the apparatus at any place.

Socket outlets providing mains power to other apparatus should be marked with the power and current that can be drawn. If only one terminal is provided for supply to other apparatus, the marking can be put on the apparatus at any place.

Controls and indicators

Marking and indication for switches and other controls should be located either:

1. On or adjacent to the switch or control, or
2. Elsewhere, provided it is obvious to which switch or control the marking applies.

Indicators used for this purpose should, whenever practicable, be comprehensible without the knowledge of language, national standard, etc.