

Fig. 7: Eagle default pad size and shape for jumper diameter of 1.6mm (0.063 inch) and drill size of 0.8mm (0.032 inch)




Fig. 8: Recommended pad size and shape for jumper




Fig. 9: Eagle default pad size and shape for header blocks




Fig. 10: Header block recommendations: circular pad shape; pad diameter of 1.9304mm or 0.076-inch; pad drill size of 0.7mm or 0.02755906 inch

8 shows the recommended pad size and shape for jumpers. These specifications can also be used for through-hole components like resistors, capacitors and transistors. The recommended diameter is 0.1 inch and drill size is 0.032 inch. Drill size may be reduced to 0.027 inch. Though this drill size is really small, it creates a very small drill

centre in the pad, which is very useful for positioning the drill bit precisely in the centre of the pad. Use either round or octagon shape for pads.

For connectors like header blocks that have single-in-line or dual-in-line pins, refer to Eagle default pad size and shape in Fig. 9. Use the recommendations in Fig.




Fig. 11: Header block recommendations: Octagon pad shape; pad diameter of 1.9304mm or 0.076 inch; pad drill size of 0.7mm or 0.02755906 inch




Fig. 12: Solder bridges between the pads when you use larger size




Fig. 13: Eagle default IC pad size and shape




Fig. 14: Recommended IC pad size and shape—pad diameter of 1.9304mm or 0.076 inch; pad drill size of 0.7mm or 0.02755906 inch

10 or Fig. 11. The two differ only in the pad shape. The recommendation is pad diameter of 1.9304mm (0.076 inch) and pad drill size of 0.7mm (0.02755906 inch). If you go overboard and use a larger pad size of 2.1844mm (0.086 inch) as shown in Fig. 12, you run the risk of having solder bridges between the pads.