



Hewlett Packard
Enterprise

Technical Documentation

HPE Synergy ImageStreamer ESXi Artifact Bundle Documentation

Edition: 1
Published: March 2017



**Hewlett Packard
Enterprise**

Technical Documentation

Notices

The information contained herein is subject to change without notice. The only warranties for Hewlett Packard Enterprise products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty.

Hewlett Packard Enterprise shall not be liable for technical or editorial errors or omissions contained herein. Confidential computer software. Valid license from Hewlett Packard Enterprise required for possession, use, or copying. Consistent with FAR 12.211 and 12.212, Commercial Computer Software, Computer Software Documentation, and Technical Data for Commercial Items are licensed to the U.S. Government under vendor's standard commercial license.

Links to third-party websites take you outside the Hewlett Packard Enterprise website. Hewlett Packard Enterprise has no control over and is not responsible for information outside the Hewlett Packard Enterprise website.

Table of contents

1 HPE Synergy Image Streamer ESXi Artifact Bundle	4
1.1 Introduction	4
1.2 ESXi Build Plans	4
1.2.1 Deploy Build Plan: HPE - ESXi - simple host configuration	4
1.2.2 Deploy Build Plan: HPE - ESXi - simple host configuration with NIC HA	6
1.2.3 Deploy Build Plan: HPE - ESXi - deploy in multi frame config	9
1.2.4 Capture Build Plan: HPE - ESXi - generalize full state	11
1.3 ESXi Plan Scripts	11
1.3.1 HPE - ESXi - mount	11
1.3.2 HPE - ESXi – unpack state	12
1.3.3 HPE - ESXi - configure management 1st NIC	12
1.3.4 HPE - ESXi - configure management 2nd NIC HA	13
1.3.5 HPE - ESXi - configure iSCSI boot HA	13
1.3.6 HPE - ESXi - set password	13
1.3.7 HPE - ESXi - configure ssh	13
1.3.8 HPE - ESXi - repack state	14
1.3.9 HPE - ESXi – umount	14
1.3.10 HPE - ESXi – generalize full state	14
1.4 Create ESXi golden image using ImageStreamer	15

1 HPE Synergy Image Streamer ESXi Artifact Bundle

1.1 Introduction

HPE Synergy ImageStreamer ESXi Artifact Bundle includes artifacts to deploy and capture ESXi. The following ESXi versions are supported by ESXi artifact bundle.

- ESXi 5.5
- ESXi 6.0
- ESXi 6.5

Hewlett Packard Enterprise does not ship ESXi golden images as part of ESXi artifact bundle. In order to use ESXi artifact bundle, an existing ESXi golden image should be added to ImageStreamer appliance or use ImageStreamer functionality to install and capture an ESXi image as explained in section “1.4”.

1.2 ESXi Build Plans

1.2.1 Deploy Build Plan: HPE - ESXi - simple host configuration

Deploys ESXi with a single ESXi management NIC configuration. The following parameters can be personalized using this build plan:

- hostname
- domain name
- root password
- enable SSH
- ESXi management NIC configuration - DHCP or static

Steps: Plan Script Names	Attributes
HPE - ESXi - mount	(none)
HPE - ESXi - unpack state	(none)

HPE - ESXi - configure management 1st NIC	DomainName Hostname ManagementNIC.mac ManagementNIC.ipaddress ManagementNIC.netmask ManagementNIC.gateway ManagementNIC.vlanid ManagementNIC.dns1 ManagementNIC.dns2
HPE - ESXi - set password	Password
HPE - ESXi - configure ssh	SSH
HPE - ESXi - repack state	(none)
HPE - ESXi - umount	(none)

Step 1: HPE - ESXi - mount

Mounts ESXi partition 5 (/bootbank) so that ESXi configuration files can be accessed for personalization.

Step 2: HPE - ESXi – unpack state

ESXi stores its configuration files in a compressed tar archive format (.tgz file) in /bootbank area. This build step downloads and extracts ESXi configuration files such as onetime.tgz or state.tgz, boot.cfg files from /bootbank area and keeps it ready for personalization

Step 3: HPE - ESXi - configure management 1st NIC

Prerequisite: During server profile creation, ESXi management connection should be added after selecting OS deployment plan so that ESXi management connection appears after the deployment connections in '**Connections**' part of Server Profile.

This step configures ESXi with a management NIC either with DHCP or static values. It adds a new vswitch '**vswitch1**' with uplink corresponding to ESXi management NIC and portgroup-name '**ManagementNetwork1**'. A new network interface '**vmk2**' is created with portgroup-name '**ManagementNetwork1**'.

This step also configures host name and domain name of ESXi host.

Step 4: HPE - ESXi - set password

Set password for ESXi root user.

Note: Password values should meet password complexity requirements defined for ESXi 5.x and ESXi 6.x appropriately. For details, please refer 1.3.6.

Step 5: HPE - ESXi - configure ssh

Enables SSH access to ESXi host.

Step 6: HPE - ESXi - repack state

Updates onetime.tgz or state.tgz with local.sh containing personalization commands and uploads it to the ESXi /bootbank area

Step 7: HPE - ESXi – umount

Unmounts ESXi /bootbank partition

1.2.2 Deploy Build Plan: HPE - ESXi - simple host configuration with NIC HA

Deploys ESXi with two ESXi management NICs in HA configuration. Also enables HA on ESXi for iSCSI boot from Image Streamer. The following parameters can be personalized using this build plan.

- hostname
- domain name
- root password
- enable SSH
- ESXi management NIC 1 configuration - DHCP or static
- add ESXi management NIC 2 in HA mode

Steps: Plan Script Names	Attributes
HPE - ESXi – mount	(none)
HPE - ESXi - unpack state	(none)
HPE - ESXi - configure management 1st NIC	DomainName Hostname ManagementNIC.ipaddress ManagementNIC.netmask ManagementNIC.gateway ManagementNIC.dns1 ManagementNIC.dns2

HPE - ESXi - configure management 2nd NIC HA	ManagementNIC2.mac
HPE - ESXi - set password	Password
HPE - ESXi - configure ssh	SSH
HPE - ESXi - repack state	(none)
HPE - ESXi – umount	(none)

Step 1: HPE - ESXi - mount

Mounts ESXi partition 5 (/bootbank) so that ESXi configuration files can be accessed for personalization.

Step 2: HPE - ESXi – unpack state

ESXi stores its configuration files in a compressed tar archive format (.tgz file) in /bootbank area. This build step downloads and extracts ESXi configuration files such as onetime.tgz or state.tgz, boot.cfg files from /bootbank area and keeps it ready for personalization

Step 3: HPE - ESXi - configure management 1st NIC

Prerequisite: During server profile creation, ESXi management connection should be added after selecting OS deployment plan so that ESXi management connection appears after the deployment connections in '**Connections**' part of Server Profile.

This step configures ESXi with a management NIC either with DHCP or static values. It adds a new vswitch '**vswitch1**' with uplink corresponding to ESXi management NIC and portgroup-name '**ManagementNetwork1**'. A new network interface '**vmk2**' is created with portgroup-name '**ManagementNetwork1**'.

This step also configures host name and domain name of ESXi host.

Step 4: HPE - ESXi - configure management 2nd NIC HA

This step also adds an uplink corresponding to second ESXi management connection to vSwitch1 created in Step 3.

Step 5: HPE - ESXi - set password

Set password for ESXi root user.

Note: Password values should meet password complexity requirements defined for ESXi 5.x and ESXi 6.x appropriately. For details, please refer 1.3.6.

Step 6: HPE - ESXi - configure ssh

Enables SSH access to ESXi host

Step 7: HPE - ESXi - repack state

Updates onetime.tgz or state.tgz with local.sh containing personalization commands and uploads it to the ESXi /bootbank area

Step 8: HPE - ESXi – umount

Unmounts ESXi /bootbank partition

1.2.3 Deploy Build Plan: HPE - ESXi - deploy in multi frame config

Deploys ESXi with HA configuration for iSCSI boot connections in a multi-frame environment containing a pair of ImageStreamer appliances. The following parameters can be personalized using this build plan

- hostname
- domain name
- root password
- enable SSH
- ESXi management NIC configuration - DHCP or static

Steps: Plan Script Names	Attributes
HPE - ESXi - mount	(none)
HPE - ESXi - unpack state	(none)
HPE - ESXi - configure management 1st NIC	DomainName Hostname ManagementNIC.mac ManagementNIC.ipaddress ManagementNIC.netmask ManagementNIC.gateway ManagementNIC.vlanid ManagementNIC.dns1 ManagementNIC.dns2
HPE - ESXi - configure iSCSI boot HA	(none)
HPE - ESXi - set password	Password
HPE - ESXi - configure ssh	SSH
HPE - ESXi - repack state	(none)
HPE - ESXi - umount	(none)

Step 1: HPE - ESXi - mount

Mounts ESXi partition 5 (/bootbank) so that ESXi configuration files can be accessed for personalization.

Step 2: HPE - ESXi – unpack state

ESXi stores its configuration files in a compressed tar archive format (.tgz file) in /bootbank area. This build step downloads and extracts ESXi configuration files such as onetime.tgz or state.tgz, boot.cfg files from /bootbank area and keeps it ready for personalization

Step 3: HPE - ESXi - configure management 1st NIC

Prerequisite: During server profile creation, ESXi management connection should be added after selecting OS deployment plan so that ESXi management connection appears after the deployment connections in 'Connections' part of Server Profile.

This step configures ESXi with a management NIC either with DHCP or static values. It adds a new vswitch '**vswitch1**' with uplink corresponding to ESXi management NIC and portgroup-name '**ManagementNetwork1**'. A new network interface '**vmk2**' is created with portgroup-name '**ManagementNetwork1**'.

This step also configures host name and domain name of ESXi host.

Step 4: HPE - ESXi - configure iSCSI boot HA

Prerequisite: During server profile creation, ESXi management connection should be added after selecting OS deployment plan so that ESXi management connection appears after the deployment connections in 'Connections' part of Server Profile.

This step adds a 2nd deployment uplink '**vmnic1**' to vSwitch0. This step configures vSwitch0 to enable HA on ESXi for iSCSI boot from Image Streamer.

Step 4: HPE - ESXi - set password

Set password for ESXi root user.

Note: Password values should meet password complexity requirements defined for ESXi 5.x and ESXi 6.x appropriately. For details, please refer 1.3.6.

Step 5: HPE - ESXi - configure ssh

Enables SSH access to ESXi host.

Step 6: HPE - ESXi - repack state

Updates onetime.tgz or state.tgz with local.sh containing personalization commands and uploads it to the ESXi /bootbank area

Step 7: HPE - ESXi – umount

Unmounts ESXi /bootbank partition

1.2.4 Capture Build Plan: HPE - ESXi - generalize full state

Performs full generalization of an ESXi image without retaining any of the ESXi host configuration.

Steps: Plan Script Names	Attributes
HPE – ESXi – mount	(none)
HPE – ESXi – generalize host configuration	(none)
HPE – ESXi – umount	(none)

Step 1: HPE - ESXi - mount

Mounts ESXi partition 5 (/bootbank) so that ESXi configuration files can be accessed for generalization.

Step 2: HPE - ESXi – generalize full state

Perform full generalization of ESXi host configuration by doing the following:

- empty the contents of jumpstrt.gz and useropts.gz files
- delete state.tgz file
- edit boot.cfg to point to onetime.tgz instead of state.tgz

Step 3: HPE - ESXi – umount

Unmounts ESXi /bootbank partition

1.3 ESXi Plan Scripts

1.3.1 HPE - ESXi - mount

ESXi stores its configuration files (state.tgz, onetime.tgz, boot.cfg etc) in /bootbank partition (partition no. 5). This planscript mounts this ESXi /bootbank partition so that ESXi configuration files can be accessed for personalization/generalization.

Attributes:

(none)

1.3.2 HPE - ESXi – unpack state

ESXi stores its configuration files in a compressed tar archive format (.tgz file) in /bootbank area. This planscript downloads and extracts ESXi configuration files such as onetime.tgz, state.tgz, boot.cfg files from /bootbank area and keeps it ready for personalization.

Attributes:

(none)

1.3.3 HPE - ESXi - configure management 1st NIC

Configures ESXi with a management NIC either with DHCP or static values. It adds a new vswitch 'vswitch1' with uplink corresponding to ESXi management NIC and portgroup-name 'ManagementNetwork1'. A new network interface 'vmk2' is created with portgroup-name 'ManagementNetwork1'.

This step also configures host name and domain name of ESXi host.

This planscript writes esxcli commands corresponding to above configuration into local.sh so that this configuration takes effect during first boot of ESXi.

Attributes:

DomainName (FQDN)

Fully Qualified Domain Name of ESXi host

Hostname (Hostname)

Host name for the ESXi host

ManagementNIC (NIC)

ESXi management NIC configuration, either DHCP or static. In case of static, the following values needs to be specified during deployment.

- ManagementNIC.ipaddress
- ManagementNIC.netmask
- ManagementNIC.gateway
- ManagementNIC.vlanid
- ManagementNIC.dns1
- ManagementNIC.dns2
- ManagementNIC.mac

Mac address corresponding to ESXi management network connection. Set automatically by Server profile.

1.3.4 HPE - ESXi - configure management 2nd NIC HA

This step adds an uplink corresponding to second ESXi management connection to vSwitch1.

Attributes:

ManagementNIC2.mac

Mac address corresponding to second ESXi management network connection. Set automatically by Server profile.

1.3.5 HPE - ESXi - configure iSCSI boot HA

This step adds a 2nd deployment uplink 'vmnic1' to vSwitch0. This step configures vSwitch0 to enable HA on ESXi for iSCSI boot from Image Streamer.

Attributes:

(none)

1.3.6 HPE - ESXi - set password

Set password for ESXi root user.

Attributes:

Password (Password)

Password value for ESXi root user. Note that password value should meet password complexity requirements defined for ESXi 5.x, ESXi 6.x appropriately.

For details, please refer

<https://pubs.vmware.com/vsphere-55/index.jsp?topic=%2Fcom.vmware.vsphere.security.doc%2FGUID-DC96FFDB-F5F2-43EC-8C73-05ACDAE6BE43.html>

<https://communities.vmware.com/docs/DOC-31941>

1.3.7 HPE - ESXi - configure ssh

Enables SSH access to ESXi host.

Attributes:

SSH (Option)

enabled – enables and starts SSH service in ESXi host. Also enables and starts ESXi shell

1.3.8 HPE - ESXi - repack state

Updates onetime.tgz or state.tgz with local.sh containing personalization commands and uploads it to the ESXi /bootbank area.

Attributes:

(none)

1.3.9 HPE - ESXi – umount

Unmounts ESXi /bootbank partition.

Attributes:

(none)

1.3.10 HPE - ESXi – generalize full state

Perform full generalization of ESXi host configuration by doing the following:

- empty the contents of jumpstrt.gz and useropts.gz files
- delete state.tgz file
- edit boot.cfg to point to onetime.tgz instead of state.tgz

Attributes:

(none)

1.4 Create ESXi golden image using ImageStreamer

The following process explains how to create an ESXi golden image using Image Streamer.

1. Ensure that you have access to HPE provided ESXi ISO installation file containing iSCSI device drivers.
2. Create a server profile with “HPE - Foundation 1.0 - create empty OS Volume” as OS Deployment plan and any available server hardware. Set an appropriate value for volume size in MiB units. The Synergy Server will be configured for access to this empty OS Volume.
3. Launch iLO Integrated Remote Console of this server and set ESXi ISO file as virtual CD-ROM/DVD image file. Power on the server.
4. ESXi installation starts and ESXi installer detects the configured empty OS Volume as an iSCSI disk device. Select this iSCSI disk device as the target for ESXi installation.
5. Follow onscreen instructions and complete the ESXi installation.
6. Power off the server.
7. Navigate to ImageStreamer -> Golden Images and Click ‘Create Golden image’
8. Select the OS volume corresponding to the server profile created for empty OS volume and choose “HPE – ESXi – generalize full state” as the capture build plan.
9. ImageStreamer generalizes and captures ESXi image and adds it as a golden image.