

Event types

 For a deeper look at the firmware, please see [🔗Firmware & Protocol Specification](#) .

 [SENS-5745: Mapping table for events / human readable messages for updated S037 and S042 emails and new SMS S037S and S042S.](#) READY FOR RELEASE

{HumanReadableMessage} - Event Human Readable Message to be updated with the NEW Human Readable Message below

Event Name		When does it Happen	NEW Human Readable Message
ALERT	ON	When a smoke alarm detects smoke, or a water leak detector detects water (ALERT ON)	{Device_Type} in {location} detected {type}
ALERT	OFF	when they no longer detect smoke / water respectively (ALERT OFF).	{Device_Type} in {location} no longer detected {type}
TAMPERED	ON	When a smoke alarm is opened or water leak detector is moved out of its upright position (TAMPERED ON),	{Device_Type} in {location} was tampered
TAMPERED	OFF	when the smoke alarm is closed or water leak sensor put back into its correct orientation. (TAMPERED OFF)	{Device_Type} in {location} was no longer tampered
HUSH	ON	The HUSH button has been pressed to hush a smoke alarm (HUSH ON)	{Device_Type} in {location} hushed

HUSH	OFF	after the 8 minute timeout expires and the alarm will sound again. (HUSH OFF)	{Device_Type} in {location} no longer hushed
LOW_BATTERY (HUB)	ON	This is triggered every time a Hub or reaches critical battery levels: 15%, 10% and 5%	{Device_Type} in {location} reported a low battery level of {battery}%
LOW_BATTERY (ALARM)	ON	This is triggered every time an Alarm reaches critical battery levels: 5%	{Device_Type} in {location} reported a low battery level of {battery}%
DISCONNECT	ON	If a paired alarm fails to respond to the Hub's internal heartbeat connectivity check that is triggered every five minutes.	{Device_Type} in {location} was disconnected
RECONNECT	ON	When a paired alarm that previously was disconnected responds to a Hub's internal heartbeat connectivity check that is triggered every five minutes.	{Device_Type} in {location} was reconnected
BATTERY	ON	A query response to update battery life of both the hub and all paired alarms. This is triggered before a full test, and every time the hub successfully responds to a VERIFY command.	{Device_Type} in {location} is on battery power

PREVIOUS INFORMATION

Event Name	When does it happen?	PREVIOUS Human Readable Message
ALERT	When a smoke alarm detects smoke, or a water leak detector detects water (ALERT ON), and when they no longer detect smoke / water respectively (ALERT OFF).	Alarm in {location} detected {type} Alarm in {location} no longer detected {type}
TAMPERED	When a smoke alarm is opened or water leak detector is moved out of its upright position (TAMPERED ON), and when the smoke alarm is closed or water leak sensor put back into its correct orientation. (TAMPERED OFF)	Alarm in {location} was tampered Alarm in {location} was no longer tampered
FAULT	The internal smoke chamber detects a physical issue with its ability to function. This requires a hardware replacement.	
HUSH	The HUSH button has been pressed to hush a smoke alarm (HUSH ON) and after the 8 minute timeout expires and the alarm will	Alarm in {location} hushed Alarm in {location} no longer hushed

	sound again. (HUSH OFF)	
ALARMS	This is a query/response from the Hub that lists all paired alarms. This is triggered before a full test, and every time the hub successfully responds to a VERIFY command.	Hub reported back {count} alarms in: {location}
VERIFY	The Hub heartbeat query/response. Every 24 hours every hub is sent a VERIFY command, and will respond with a corresponding VERIFY response if connected.	Hub connection status verified. Hub did not respond
BATTERY	A query response to update battery life of both the hub and all paired alarms. This is triggered before a full test, and every time the hub successfully responds to a VERIFY command.	Hub battery level is {battery}% Alarm in "{location}" battery level is {battery}%
LOW_BATTERY	This is triggered every time a Hub or Alarm reaches critical battery levels: 15%, 10% and 5%.	Hub reported a low battery level of {battery}% Alarm in {location} reported a low battery level of {battery}%

TEST	One TEST event is sent to the Hub to initiate a full test of all paired alarms. Each paired alarm will then respond with a TEST success or TEST failure within five minutes.	Alarm in {location} reported a {status} test
RECONNECT	When a paired alarm that previously was disconnected responds to a Hub's internal heartbeat connectivity check that is triggered every five minutes.	Alarm in {location} was reconnected
DISCONNECT	If a paired alarm fails to respond to the Hub's internal heartbeat connectivity check that is triggered every five minutes.	Alarm in {location} was disconnected
POWER	When a hub changes between AC and battery power. This will either happen due to power failing or being restored, or unplugging / replugging the hub power cable.	Hub switched to {status}
REBOOT	A hub has rebooted.	
RESET	A hub has been factory reset.	
ADD	Triggered when initiating a new alarm /	Alarm added in {location}

	device being paired with the Hub. This will respond with success or failure. This usually fails if the user forgets to put the alarm into pairing mode by double-tapping the TEST button.	
REMOVE	Triggered when removing an alarm / device from a Hub. This will respond with success or failure. This would only fail in rare circumstances, most likely during testing if the alarm has already been removed from the hub.	Alarm removed from {location}

b. {Device_Type} and {type} relationship

Device Type	{Device_Type}	{type}
Sensor Hub	Hub	
Smoke Alarm	Smoke Alarm	smoke
Water Leak Detector	Water Leak Detector	water
Smoke + CO Alarm	Smoke + CO Alarm	carbon monoxide (note, this is for the CO alert type)

4. **Update the triggers for the sending of S037 and S042** for when any of the events above are triggered, the email S037 gets sent to Agent and S042 gets sent to Tenant.

FOR EXAMPLE: If A smoke alarm in the hallway of a property sets off an alert because it detects smoke,
the emails will read as below (and all text underlined is for demonstration purposes of the fields/text and will NOT appear as underlined in the actual message created).

S037:

Subject: Alert - 123 Happy Street, West Gosford NSW 2250 - Smoke Alarm in hallway detected smoke

The Smoke Alarm in hallway detected smoke at 123 Happy Street, West Gosford NSW 2250.
Please navigate to your Sensor Portal to action.

Kind regards,
Sensor Support Team

S042:

Subject: Alert - 123 Happy Street, West Gosford NSW 2250 - Smoke Alarm in hallway detected smoke

The Smoke Alarm in hallway detected smoke at 123 Happy Street, West Gosford NSW 2250.
Please take the appropriate action, and if any further assistance is required call us on 1300 000 944.

Kind regards,
Agency

EMAILS that are affected in this change S037, S042 (Changed), S038, S041, S095 and S096 (Stopped).