

1. A user reports their laptop won't power on ever, when plugged in. List 5 troubleshooting steps you would take to diagnose the cause, and for each step, explain what are you checking for.

-
1. check the outlet & charger :-
make sure the wall outlet works and the charging cable isn't damaged / loose.
 2. Look for status lights :-
See if laptop's charging light turns on to confirm power actually reach motherboard.
 3. perform a Hard Reset :-
unplug everything, hold power button for 30 seconds and reconnect power to drain stuck static electricity.
 4. Inspect the screen :-
listen to fan noise or look close with flashlight to check laptop is on but screen is just black.
 5. test the Battery :-
if laptop has removable battery, pop it out and plug charger in alone to see if dead battery is blocking power.

2. you receive a helping desk ticket & 'my monitor is showing a blank screen, but the CPU seems to be running'. write a step-by-step troubleshooting flow you would follow to identify and resolve the issue.

-
1. check power & physical cables
 2. verify monitor input & display settings (monitor control).
 3. Test with Alternative devices.
 4. check internal PC components

3. A user complains that their wireless mouse is unresponsive, but the keyboard works fine. describe how you would isolate whether the issue is with the mouse, the USB port, or the system settings.

-
1. Test the mouse &
check the mouse switch is on, mouse has fresh battery and sensor light underneath glows when moved.

2. Test USB port &

move USB dongle to different port or plug flash drive into the old port to see if the port is actually works.

3. Test system settings :-

open device manager, uninstall mouse under "mice and other pointing devices" and re-plug the cable to refresh the driver.

4. cross-test on Another pc :-

plug mouse in different pc if it work there then your original pc has software if it fails there too then mouse is dead.

4. Imagine you are working on a helpdesk team for a gaming cafe. one system is overheating and shutting down during use. List 3 possible hardware causes and describe how you could check each one.



1. Check Blocked Fans :-

check pc's case fan and cpu cooler for dust buildup and spin them by hand while it's off to check if fan turn freely or sticking.

2. Failing / unplugged fans :-

Power on system and physically watch that the cpu cooler fan & graphics card fan spin up & blow air under load properly or not.

3. Dried-out Thermal paste :-

Remove cpu cooler to check thermal paste underneath if it is cracked, dry or crusty clean it off with isopropyl alcohol and reapply fresh paste.