

INTEGRATION NOTE

Sky Stream / Sky Glass — Crestron Home Driver

Manufacturer:	Sky
Model(s):	Sky Stream, Sky Glass
Device Type:	Cable Box
Control Platform:	Crestron Home (4-Series processors, e.g. CP4-R)
Tested Crestron Home Version:	4.010.0016
Connection:	Ethernet (IP), TCP port 8091
Driver Developer:	Home Ergonomic Programming
Document Revision Date:	9 July 2026

OVERVIEW

This driver allows a Crestron Home system to control Sky Stream pucks and Sky Glass TVs over the local network, providing navigation and transport control.

The driver connects directly to the Sky device over a secure IP connection on TCP port 8091 and pairs with it automatically. No configuration is required on the Sky device itself.

SUPPORTED FEATURES

Navigation & Transport control:

- Power toggle
- Cursor Up, Down, Left & Right
- Select & Back
- Guide, Menu & Info
- Channel Up & Down
- Direct channel selection (supports Crestron Home channel presets / favourites)
- Number keys 0 – 9
- Colour buttons (Red, Green, Yellow, Blue)
- Play / Pause
- Fast Forward & Rewind
- Record

Control is one-way: the driver does not report power, channel or playback status back to the Crestron Home system.

ANY FEATURE NOT SPECIFICALLY NOTED AS SUPPORTED SHOULD BE ASSUMED TO BE UNSUPPORTED.

DRIVER LICENCE

This driver requires a licence key to function. Licences are issued on a per-controller basis: a single licence covers all instances of the driver on the same control processor, so multiple Sky devices controlled from one processor require only one licence.

Licences can be purchased <http://home-ergonomic-programming.co.uk/>. Payment is processed securely by Polar, our merchant of record, and your licence key is emailed to you automatically as soon as the purchase completes.

Enter the licence key when adding the driver (or later via the device's Installer Settings). The driver activates the licence automatically over the internet and locks it to that processor. The control processor therefore requires internet access for licence activation and periodic licence validation.

DEVICE SETUP

Set up the Sky Stream puck or Sky Glass TV as per the manufacturer's instructions and connect it to the same local network as the Crestron Home processor.

A static IP address (or a DHCP reservation) is required so that the address entered in Crestron Home does not change.

Ensure that no firewall or VLAN rule blocks TCP port 8091 between the Crestron Home processor and the Sky device.

The Sky device must be powered on (not in deep standby) when the driver is first added, so that the initial automatic pairing can complete.

INSTALLATION PROCESS

1. Copy the driver package (.pkg) file to the Crestron Home processor. Connect to the processor via SFTP (Crestron Home enforces secure file transfer) using a tool such as Crestron Toolbox or FileZilla, and copy the file into the following directory:

`/user/ThirdPartyDrivers/Import`

2. Crestron Home will import the driver automatically. This may take a few minutes; once imported, the file will disappear from the Import directory.

3. In the Crestron Home Setup app, add the driver to the appropriate room. It can be found under *Drivers -> Cable Box -> Sky*. Enter a descriptive name and the IP address of the Sky device. Leave the IP port at its default (8091) and leave "Requires Authentication" unchecked, then confirm.

4. Assign the Sky device's HDMI output to a display in the Source Routes page so it appears as a selectable source.

5. Optionally, configure your local TV provider in Crestron Home to make use of the channel preset / favourites features.

COMMON MISTAKES

1. Incorrect IP address entered.
2. TCP port 8091 blocked between the processor and the Sky device by a firewall or VLAN rule.
3. The Sky device was in deep standby when the driver was first added. Power the device on fully and allow the driver to reconnect.
4. If the Sky device stops accepting control after repeated failed connection attempts, restart the Sky device (power-cycle it at the mains) and allow the driver to reconnect.
5. Licensing errors are usually caused by the processor lacking internet access. Check that the processor has a working DNS server and that outbound HTTPS (TCP port 443) to api.polar.sh is not blocked.

SUPPORT

If you have any issues with the driver or installation that are not addressed in this document, please contact support@home-ergonomic-programming.co.uk and include as much detail about the issue as possible, including a recent processor error log.

DISCLAIMER

This driver is developed and supplied by Home Ergonomic Programming. It is an independent product: Home Ergonomic Programming is not affiliated with, endorsed by or connected to Sky.

Sky, Sky Stream and Sky Glass are trademarks of their respective owners.

By purchasing a licence for, installing or using this driver you agree to the Terms and Conditions set out at the end of this document. The driver is provided without warranty of any kind; you should always carry out your own testing before first use in a live system.

TERMS AND CONDITIONS

These Terms and Conditions ("Terms") apply to the sale of licences for, and the supply and use of, the Sky Stream / Sky Glass Crestron Home driver. Please read them carefully before purchasing a licence or installing the software. If you do not agree to these Terms, do not purchase, install or use the software.

1. About us

- 1.1 The software is developed and supplied by Home Ergonomic Programming ("we", "us", "our").
- 1.2 You can contact us by email at HomeErgonomicProgramming@proton.me.

2. The software

- 2.1 These Terms apply to the Sky Stream / Sky Glass Crestron Home driver, together with any updates or new versions we may supply (the "Software").
- 2.2 The Software is licensed to you, not sold. All intellectual property rights in the Software remain our property at all times, including after installation on your equipment.

3. Licence

3.1 The Software requires a licence key to function. Licences are issued on a per-controller basis: a single licence covers all instances of the Software on the same control processor. The licence key is activated over the internet and locked to the first control processor on which it is used.

3.2 Subject to payment of the applicable licence fee, we grant you a non-exclusive, non-transferable, limited, revocable licence to install and use the Software on the control processor specified at the time of purchase. The number of installations must not exceed the number of licences you have purchased.

3.3 A licence is valid only for the specific control processor identified at the time of purchase and may not be resold or transferred to any other system. In exceptional circumstances we may, at our sole discretion, authorise the transfer of a licence to a new system, and we reserve the right to charge an administrative fee for this service or to refuse authorisation.

3.4 You may not copy (except as reasonably necessary for installation and backup), distribute, sell, sub-license, rent or lease the Software to any third party without our prior written consent.

3.5 You may not decrypt, decompile, disassemble, reverse engineer, translate, modify or create derivative works of the Software, in whole or in part. Any breach of this clause will immediately terminate all licences held by you.

3.6 Licence activation and periodic licence validation require the control processor to have internet access. We are not liable for any interruption to the operation of the Software caused by network restrictions, firewall rules or DNS failures at the installation site that prevent communication with the licensing service.

4. Ordering and payment

4.1 The Software is designed to be installed and configured by qualified system integrators for the Crestron Home platform. We sell business-to-business only and do not licence the Software to end consumers. By purchasing a licence you confirm your status as a qualified system integrator. If you are the owner of a system and believe you require the Software, please contact your system integrator, who can obtain a licence and carry out the integration work on your behalf.

4.2 Licences can be purchased from <http://home-ergonomic-programming.co.uk/>. All purchases are processed by Polar (polar.sh), acting as merchant of record. Polar handles payment processing and the calculation, collection and remittance of any applicable VAT or sales taxes, and issues the receipt for your purchase. We do not see, handle or store your payment card details.

4.3 Prices are as displayed at checkout and are exclusive of any applicable taxes, which are calculated and added at checkout by the merchant of record. We reserve the right to amend prices, or to withdraw the Software from sale, at any time.

4.4 Please ensure the details you provide when ordering are complete and correct; we cannot be held responsible for any delays or losses caused by incorrect information being supplied. A contract between you and us for the licence of the Software exists once you have received your licence key.

5. Delivery

5.1 The Software is supplied by download only; it is not available in any physical format and there are no delivery charges. Licence keys are delivered automatically by email by the merchant of record on completion of purchase, to the address given at the time of ordering. Please check your spam folder before contacting us regarding a missing licence key.

6. Refunds

6.1 We do not generally offer refunds on licensing. If you have made a mistake during your purchase, or have another legitimate reason for requiring a refund, please contact us as soon as possible using the details in clause 1.2. A refund may be offered within 7 working days of purchase in some circumstances, but no refund will be considered once the Software has been installed on the relevant control processor. Refunds are processed by the merchant of record and may additionally be subject to its terms.

7. Third-party devices and services

7.1 The Software controls equipment and services provided by third parties. Sky, Sky Stream and Sky Glass are trademarks of their respective owners. We are not affiliated with, endorsed by or connected to Sky in any way.

7.2 The operation of the Software depends on the behaviour of the Sky device and its associated services, which may be changed, updated or withdrawn by the manufacturer at any time and without notice. We are not responsible for any loss of functionality caused by such changes, although we will use reasonable endeavours to restore functionality where practicable.

7.3 We reserve the right to modify, suspend or withdraw the Software at any time and for any reason, including where the equipment or service it controls is discontinued or substantially modified.

8. Warranty disclaimer

8.1 The Software is provided “as is” and “as available”, without any warranty, condition or representation of any kind, whether express or implied, to the maximum extent permitted by law, including without limitation any implied warranties of satisfactory quality, fitness for a particular purpose and non-infringement.

8.2 We do not warrant that the Software will meet your requirements, that its operation will be uninterrupted, timely, secure or error-free, or that any defects will be corrected.

8.3 Whilst every care is taken in the development and testing of the Software, you must always carry out your own testing in the target system before first use. You are solely responsible for verifying the Software's suitability for your project.

9. Limitation of liability

9.1 Nothing in these Terms excludes or limits our liability for death or personal injury caused by our negligence, for fraud or fraudulent misrepresentation, or for any other liability that cannot be excluded or limited under English law.

9.2 Subject to clause 9.1, we shall not be liable, whether in contract, tort (including negligence) or otherwise, for any indirect or consequential loss, loss of profit, loss of business, loss of data, or damage to computer systems or control platforms, arising out of or in connection with the installation or use of the Software.

9.3 Subject to clause 9.1, our total aggregate liability arising out of or in connection with the Software shall not exceed the amount paid by you for the licence to the Software or £100, whichever is the greater.

9.4 You install and use the Software at your own discretion and risk.

10. Support and updates

10.1 Support for the Software is provided on a reasonable-endeavours basis via the contact details in clause 1.2. When requesting support, please include as much detail as possible, including a recent processor error log.

10.2 The Software is supported for as long as it is offered for sale. We reserve the right to withdraw the Software from sale and discontinue on-going support at any time and for any reason; the remainder of your rights and obligations under these Terms will not be affected.

10.3 We may release updates to the Software from time to time, but we are under no obligation to do so.

11. Termination

11.1 The licence granted under these Terms terminates automatically if you breach any of them. On termination you must remove the Software from all control processors and destroy all copies in your possession.

12. General

12.1 These Terms constitute the entire agreement between you and us in relation to the Software.

12.2 Each of the paragraphs of these Terms operates separately. If any court or relevant authority decides that any of them is unlawful or unenforceable, the remaining paragraphs will remain in full force and effect.

12.3 This agreement is between you and us. No other person shall have any right to enforce any of these Terms.

12.4 These Terms are governed by the laws of England and Wales, and the courts of England and Wales shall have exclusive jurisdiction over any dispute arising from them.